

POPULAR

# Computing

WEEKLY

27 May 1982 Vol 1 No 6

30p

**Computer concerto**

**Reviews: Mission  
of the Deep**

**Vic-20  
printer**

**Inside  
the Spectrum**

**Function keys on Vic-20**



# ANGLO AMERICAN SOFTWARE CO

TRS-80 ≈ ATARI ≈ PET ≈ APPLE ≈ VIC ≈ ZX81 ≈ BBC

We know what it is like out there, because that's where we came from. Before we decided to become software entrepreneurs, we were just like you enthusiasts searching through magazines for the ideal mail order software source. What we hoped to find was a single entity that offered an ultra-wide selection for our micro-computer. That pre-selected only the best of many similar sounding programs that reached the market every month. That could give us personal assistance with the purchase-decision process, and that stood behind its products. When we couldn't find it we decided to become it. So **ANGLO-AMERICAN SOFTWARE CO WAS BORN.**

Please state clearly the program(s) you require. Include your name, address & machine type + memory size. Prices include VAT, postage & packing.

<p><b>OIL TYCOON</b></p> <p>What would it be like to be an oil producer. Find out with this action packed simulation as you try to become an oil tycoon. Explore for new wells, get reports, name your own price for oil — but don't get too greedy or beware. The game involves strategy and chance. You could end up as one of the wealthiest men in the country or the bankrupt victim of too many oil spills. You will find <b>OIL TYCOON</b> both challenging and exciting.</p> <p><b>PRICE £9.95p CASSETTE</b></p>	<p><b>MASTER DIRECTORY</b></p> <p>Wasn't it yesterday you threw the cat in to the washing machine because you couldn't find where you had put the last Adventure game you had saved or was it that you gave your mother-in-law the leftover curry because your three year old had mixed up all your data disks and now you don't know which one is which? Well cheer up <b>MASTER DIRECTORY</b> is here. The M.D. is a storage program that reads the files on your disks, stores the name, extension and even records the free space on each disk. All you do is number your disks. You can use it alphabetically or search for name and ext search for free space. Store 5000 files or 320 disks. Requires one disk drive.</p> <p><b>PRICE £21.00p DISK.</b></p>	<p><b>AIR FLIGHT SIMULATION</b></p> <p>Instrument takeoffs and landings are no picnic, ask any pilot. This computer simulation is sure to keep you on the edge of your seat. You begin with a full tank of fuel and a flight plan to learn simple takeoffs and landings. Pay attention to your instrument panel; too steep a bank and your air speed will drop like a stone... so will your plane. It's about as close to the real thing as you can get this side of the runway. Fun for all the family when you learn to do acrobatic manoeuvres.</p> <p><b>PRICE £9.95p CASSETTE</b></p>
<p><b>DUNGEON OF DEATH</b></p> <p>Your quest is to search for the Holy Grail where you descend through 12 levels, find the Holy Grail and return to the surface. The Grail is guarded by <b>SMAUG</b> the most fearsome monster of all and ten lesser breeds. You can only survive by using all the powers at your command. You can cast magic spells, drink potions that may or may not help you find items to help you fight the monsters. Step softly in the darkness. Treasure or sudden death is only a foot-fall away in the <b>DUNGEON OF DEATH.</b></p> <p><b>PRICE £10.75p CASSETTE</b></p>	<p><b>THE FLYING CIRCUS</b></p> <p>Is a package covering biplane to modern day planes. These seven programs offer you the daring realism of flight.</p> <ol style="list-style-type: none"><li>1. AIR FLIGHT</li><li>2. NIGHT FLIGHT</li><li>3. AIRMAIL PILOT</li><li>4. MOUNTAIN PILOT</li><li>5. O'HARE (air traffic controller)</li><li>6. APPROACH RADAR</li><li>7. JET FIGHTER PILOT</li></ol> <p>A great combined flying package. Try to master the lot.</p> <p><b>PRICE £25.00p DISK</b></p>	<p><b>SANTA PARAVIA &amp; FIUMACCIO</b></p> <p>Fancy being a Mrs. <b>THATCHER</b> — well with this program you will come as near to it as you will ever be. Perhaps I should acquaint you with the domain. It is not a wealthy area but riches and glory are there for the aware. You will have to worry about the serfs requesting more grain; if they don't get it they may flee. There is the weather as well — if it is good so will the crops be. You may find you have to increase the tax. You may also wish to build a new palace. To measure your progress, the official cartographer will draw you a map so as to see how to plan your strategy. A very entertaining game.</p> <p><b>PRICE £10.50p CASSETTE</b> <b>PRICE £14.25p DISK</b></p>

**Send 75p for full catalogue**  
(Refundable against purchase)

## ANGLO AMERICAN SOFTWARE CO

138a Stratford Road,  
Sparkhill,  
BIRMINGHAM, B11 1AG  
021-771 2995

To place orders quote your Access no.



### ★ PROGRAM OF THE MONTH ★

#### **SPACE SHUTTLE Save £4.50p**

5.3 million pounds of thrust sent the space shuttle **COLUMBIA** into orbit. Now on-board computers will help to bring her safely, and gracefully back to earth. **SPACE SHUTTLE** puts you in the command pilot's chair of the first reusable space vehicle and until commercial flight becomes available this is the closest you will get. We feel this is one of our best programs.

**PRICE £17.00 CASSETTE**

### ★ SPECIAL OFFER PRICE £12.50 ★

**DEALER ENQUIRIES WELCOME**

# POPULAR Computing WEEKLY

## The Team

### Editor

Duncan Scot

### Reporter

David Kelly [01-930 3271]

### Sub-editor

Peter Harvey

### Designer

Eric Robbie

### Editorial Secretary

Fiona McCormick

### Advertisement Manager

David Lake [01-839 2846]

### Advertisement Executive

Peter Chandler [01-839 1881]

### Software Editor

Peter Gerrard [01-839 1855]

### Publishing Director

Nick Hampshire

*Popular Computing Weekly*, Hobhouse Court, 19 Whitcomb Street, London WC2  
Telephone: **01-839 6835**

Published by Sunshine Publications Ltd.

Typesetting, origination and printing by Chesham Press, Chesham, Bucks

Distributed by S M Distribution  
London SW9. 01-274 8611. Telex: 261643

© Sunshine Publications Ltd 1982

### Subscriptions

You can have *Popular Computing Weekly* sent to your home: the subscription rate is **£19.95** per year, for addresses in the UK.

### How to submit articles

Articles which are submitted for publication should not be more than 1000 words long.

All submissions should be typed and a double space should be left between each line.


Programs should, whenever possible, be computer printed.

At present we cannot guarantee to return every submitted article, so please keep a copy.

### Accuracy

*Popular Computing Weekly* cannot accept any responsibility for any errors in programs we publish, although we will always try our best to make sure programs work.

## This Week



Cover illustration by Stuart Hughes

<b>News</b>	<b>5</b>
NewBrain relaunched at last, Vic-20 expansion box.	
<b>Club Reports</b>	<b>7</b>
Vernon Gifford reports on the Amateur Computer Club.	
<b>Computer concerto</b>	<b>8</b>
Nick Hampshire turns the Vic-20 into a piano.	
<b>Reviews</b>	<b>10</b>
Mission of the Deep, ZX keyboards.	
<b>Open Forum</b>	<b>13</b>
Six pages of programs.	
<b>Spectrum</b>	<b>19</b>
Stephen Adams looks inside the ZX Spectrum.	
<b>Programming</b>	<b>20</b>
How to use Vic-20 function keys.	
<b>Sound &amp; vision</b>	<b>21</b>
About computer art and music.	
<b>Hand &amp; mouth</b>	<b>23</b>
About languages and calculators.	
<b>Peek &amp; poke</b>	<b>25</b>
Your questions answered.	
<b>Competitions</b>	<b>26</b>
Puzzle, crossword.	

## Editorial

Why are so many of the games submitted to this magazine so blood-thirsty?

In the past couple of weeks there has been a great upsurge of programs with titles such as Falklands or Island Invasion.

It is understandable that the themes of so many programs should reflect national events.

These are still early days in home computing and most of us are still finding our way around our machines.

So we choose themes which are close to hand.

But we must look to the future.

Once we have all become more computer literate we will be able to reflect a greater imagination in our programs.

It will not be enough to be good at moving graphic blobs around the screen in fast moving chaotic patterns.

Programmers will have to know how to motivate the user, will have to understand how to play on the users' emotions, how to captivate the users' imaginations and hold them.

Blood-thirsty programs are an easy way out. Together we can raise the standard.

## Next Week



Can you survive the Black Hole? The direst doom looms on next week's event horizon. We dare you to be there.



## NewBrain debuts at less than £200

Grundy Business Systems have launched the NewBrain, at a basic-model price of £199. With an 80 or 40 column display, the system is fully expandable to over 2 megabytes.

The NewBrain is based on an original project, taken to the National Enterprise Board by Clive Sinclair. Newbury Laboratories was given the task of developing it and, finally, last year the project was sold to Grundy Business Systems, which has completed its development.

There are two models of the NewBrain available, both of which feature a full-size keyboard.

The basic Model A is built around the Z80A micro-processor with 32K RAM and 24K ROM on-board. It has dual cassette port, tv and monitor ports, an expansion

port and V24 bi-directional and printer ports.

Model AD is the same as Model A but includes an on-board blue-green vacuum fluorescent 16 character, 14 segment display.

Plug-in memory expansion modules are available for both models, with 64K, 128K, 256K or 512K of RAM. A maximum of four 512K modules may be connected, giving a total memory of over 2 megabytes.

Proprietary software packages can be used, loaded via cassette or, under CP/M®, via disc.

An important feature of the NewBrain is its size. Measuring only 11in. x 6in. x 2in. it takes up little more space than a telephone. Even with a 9in. monitor, 80 cps printer and 5¼in. floppy disc, the unit still only requires 1½ sq ft.

Andy Surtees, Grundy's



NewBrain's compact micro.

Marketing Director, says: "The NewBrain is a professional personal computer which, with a full typewriter keyboard, is designed for business, scientific and educational applications, as well as for home use."

The NewBrain is scheduled for high-volume production, available in July. Model A is £199. Model AD is £229. The 64K and 512K RAM modules are £75 and £445, respectively.

More information from Grundy Business Systems Ltd, Somerset Road, Teddington, Middlesex TW11 8TD.

## The Bee-Box gives Vic extra bytes

The Vic-20 expansion unit, manufactured by B&B Computers of Bolton, is now available.

John Blackburn, managing director of Beelines Ltd (B&B's marketing company) explained that the unit is a spin-off from B&B's Viewdata developments.

The Bee-box, as it is called, provides the Vic with extra memory and allows it to download Teletext, Viewdata and Prestel 40 x 25 pages.

Inside the Bee-box there are two cards — a 40K RAM board and the B&B VDU display colour-writer board (this is the board that B&B sell for use with the PET).

The 40K comprises maximum 32K Basic RAM with a 2K EPROM operating command system and 6K machine-code-only addressable RAM.

The lightweight unit is of the same dimensions as the Vic and is fitted with a socket to replace the Vic expansion socket which has been used to connect it.

The unit sells for £220 plus VAT and has a twelve-month guarantee, from Beelines, Freepost, Bolton BL3 6YZ.

## Buzz words from Beebug

Beebug, the Independent National User Group for the BBC micro, has published its first monthly newsletter.

Issue One contains 26 pages, densely-packed with information of interest to both the beginner and the more advanced user. There is also a review of the BBC machine, outlining special facilities, advantages and limitations.

David Graham of Beebug told *Popular Computing Weekly* that the aim was to provide impartial advice and information to BBC owners.

"We are just people who have the machines," he said.

Beebug now has more than 3,000 members and is keen to have more. Membership applications to: Beebug, Dept 1, 374 Wandsworth Road, London SW8 4TE.

## Soft-sell on Prestel

Martochoice is trying to get more software on to Prestel, following its win in the British Telecom ZX81 Prestel adapter competition.

Software manufacturers can sell their programs through Prestel by contacting British Telecom on Freephone 2043.

Enquiries concerning the adapter to Martochoice Ltd, 10 Station Close, Jersey Farm, St Albans, Herts AL4 9HT.

## Putting the boot in

Now that summer is here, everybody's mind turns to... football. Sporting Forecasts, who already offers the F4 Football Forecast Program for the Apple, PET, Sharp, TRS80 and Video Genie micros intends to produce a version for the BBC micro in time for the 1982-3 season.

Further information from Sporting Forecasts, Bureau of Information Science, Commerce House, High Street, Chalfont St Giles, Bucks.



The ZX81 interfaces with Epson... thanks to Capital.

## Capital gives ZX81 a choice of printers

Capital Computers has produced a serial/parallel interface for the ZX81, as reported last week.

The interface, designed by Mr O. Korinek, allows the ZX81 to drive most makes of printer, thus providing greater versatility than that offered by Sinclair's own printer.

At £39.95, including VAT, the module has both RS232 and Centronics interfaces. There is 2K on-board memory and driver routines in a 2716 EPROM. The Sinclair graphics keys can be used with the EPSON printer.

The interface is designed to be used with Capital Computers Expansion Motherboard or Mini-expansion board, with a maximum 64K available for RAM/ROM addressing.

A package comprising, for example, 32K RAM, serial/parallel printer interface, cable from interface to printer, and Mini-expansion board, suitable for accounting, stock control or word-processing applications, is available for £120.

Contact Capital Computers Ltd, 100 Church Street, Luton, Beds.



# MICROFEST '82

Micro Fair and Seminar for all users  
**HARDWARE. SOFTWARE. PERIPHERALS.**

ADMISSION: ADULT ..... 1.00  
CHILD (under 16) ..... 50p  
(half price with coupon)

Exhibition and other diversions for ZX, B.B.C. Micro, VIC, TRS, Sharp, Sorcerer, Video Genie, Tangerine, Nascom, Atari, Pet and Acorn user.

- 10 Free draw for MICRO computer
- 20 Club stands
- 30 Bring and Buy stall
- 40 Free parking
- 50 Review of Sinclair Spectrum
- 60 Lectures on small micro applications
- 70 Free Films
- 80 Bar and refreshments
- 90 Close to centre and Piccadilly station
- 100 Free Coffee
- 110 Facilities for the Disabled



UNIVERSITY OF MANCHESTER INSTITUTE OF SCIENCE AND TECHNOLOGY, SACKVILLE ST, MANCHESTER

SATURDAY 24 10.30 - 21.00  
SUNDAY 25 10.30 - 18.00 JULY 1982



COMPUTER BOOKS

## DON'T! by Rodnay Zaks

Dedicated to the care, preservation and correct operation of a small computer system. If you want your computer to work and keep working, this book is indispensable.

Pb 200 pages Illustrated £8.95

## INTRODUCTION TO PASCAL by Rodnay Zaks

A simple and comprehensive introduction to standard and UCSD Pascal for anyone—beginner or experienced—who wants to learn the language rapidly.

Pb 440 pages Illustrated £11.20

## YOUR FIRST COMPUTER by Rodnay Zaks

For anyone thinking about using or buying a small computer. No technical background or prior computer knowledge is assumed.

Pb 280 pages Illustrated £6.70

## INSIDE BASIC GAMES by Richard Mateosian

How to design error-free interactive BASIC games and real-time situations.

Pb 350 pages Illustrated £11.20

### ORDER FORM

Don't £ 8.95    Your First Computer £ 6.70  
Introduction to PASCAL £11.20    Inside BASIC Games £11.20

Please include £1.25 for single copy orders & £1.60 for multiples

I enclose a cheque/postal order for: Total \_\_\_\_\_

Please debit my \_\_\_\_\_ Card# \_\_\_\_\_

I wish to receive details of other SYBEX titles in stock.

Name \_\_\_\_\_ Address \_\_\_\_\_

### CASTLE HOUSE PUBLICATIONS

27 London Road, Tunbridge Wells Kent TN1 1BX. Tel: (0892) 39606

# REMOTE 'MICRO' CONTROL

Control domestic or office appliances with your micro without the need for wiring.

By using just one TX 008 you can link your micro to remote RX 018 anywhere in your home or office. This interface system works with any micro (Apple PET ZX81 etc.)

## ● TX 008 COMPUTER INTERFACE

The TX 008 is the link between your micro and any remotely located RX 018. Its function is to pass instructions from your micro to defined remote points. The TX 008 is simply plugged into the mains and connected to an output port of any micro computer.

The TX 008 comes complete with output port connections, drive software and application examples.

ZX81 users require an extra input output port module not included in the TX 008 price see code no ZX81 CP.

TX 008 price £45.00 inc. VAT

## ● RX 018 REMOTE TX INTERFACE

The RX 018 carries out instructions passed to it from your micro via the TX 008 as with the TX 008.

No wiring is necessary just plug your RX unit into any convenient mains socket and plug in the appliance.

Your micro now has control

Price £25.00 inc. VAT

Stripeland Ltd., 111 Liverpool Road, Formby, Merseyside L37 6BR.

## ● ST KIT STARTER KIT

The St Kit is a standard starter kit containing one TX 008 and two RX 018. For further expansion of your system you only require more TX 018's.

St kit price £85.00 inc. VAT

## ● CONTROL PANELS

Control panels for interface with RX 018 are available, for further details and prices tick box provided on order form.

### Order Form

TO:

Stripeland Ltd., 111 Liverpool Road, Formby, Merseyside L37 6BR.  
0704 878062

Please send me items listed.

I enclose a cheque/postal order for £ \_\_\_\_\_

Please add £2.50 P&P to your calculated total.

Name \_\_\_\_\_

Address \_\_\_\_\_

Qty	Type	Price Each £	Total
	TX 008	45.00	
	RX018	25.00	
	ST Kit	85.00	
	ZX81cp	13.90	

Total \_\_\_\_\_

Please send me details of  
1. St control panel

2. Super Control panel

Important — Please state type and make of computer

PW

# Club Reports

Is your club involved in any special projects? Use this page to tell the world about it.

## Helping people to get more from machines

*Vernon Gifford describes how the Amateur Computer Club aids micro user.*

Most micro users will have come across the Amateur Computer Club (ACC) at major shows where members co-ordinate club stands. Usually there are about 20 Clubs and User Groups (also Computer Towns) represented at shows with up to 40 machines of many different types in action.

This has become the ideal place to meet other enthusiasts for a wider exchange of views than is possible within individual groups. Prospective buyers find it particularly useful to be able to discuss the merits of computer equipment and software with impartial users who have no commercial bias.

Hundreds of enquirers at ACC's own stand have been put in touch with their nearest local Club or specialist group through the ACC Database — which covers about 250 organisations, and which will shortly be available nationwide on Prestel. These show stands are organised by the very active David Annal, who is also secretary of ACC.

The club was founded in 1972 by Mike Lord, as a newsletter group. Later, with the help of Bob Warren, the group became a club, organising visits and meetings. This led to the formation of other clubs around the country and as these developed, the ACC found itself with a new co-ordinating role to provide background services to the personal computer movement.

This, the oldest computer club in the world, began at a time when there were few micros.

It was only in 1978 that the first computer magazine appeared and so, for five years, the ACC held a unique position.

As the emphasis has switched from hardware and home-brew construction to off-the-shelf micro systems and software, the ACC has had to become more concerned with computer peo-

ple. Members now require more information for their applications whether in homes, hobbies, recreation or small businesses. Today the main function of a co-ordinating body like the ACC is to link the users to the information.

This has been achieved via *The ACCumulator* edited by Derek and Diana Fordred, it's made great strides and now Basyl Butcher has strengthened the team.

Vernon Gifford takes care of contact with national educational bodies, the BBC, TV and radio, and the computer media.

As the ACC becomes recognised in this new role, it is more likely to be consulted as *the* representative body of the large personal computer population.

Club and User Group liaison is another important part of the ACC's programme. This enables groups to share their experiences and leads to national or regional activities in specific areas where individual clubs cannot raise sufficient numbers to justify getting speakers.

### A two-way process

To encourage feedback the ACC offers to supply the six copies per year of the newsletter at the base cost of £2.00 to any club appointing a corresponding representative. Many clubs have already taken up the offer.

Various types of associate or group membership are under consideration, and some degree of regional development seems to be desirable. The first experiment — the Association of London Computer Clubs (ALCC) — which ran its third Easter Fair, under the leadership of Robin Bradbeer (who has joined the ACC Committee) has been extremely successful.

As these new activities expanded direct mailshots to clubs have complemented news in the *ACCumulator*.

The ACC supports new groups dur-

Write to Club Reports, *Popular Computing Weekly*, Hobhouse Court, 19 Whitcomb Street, London WC2 7HF, with details of successes you have had with your club, with ideas for helping clubs along and with any news of special meetings. We look forward to hearing from you.



*Communicating . . . Vernon Gifford*

ing their formation, and, if necessary, until such time as they are self-sufficient.

National conferences or workshops are another interesting feature. Last November about 85 people attended a "Micro-Robotics" conference at Imperial College, displaying everything from Micro-Mouse to hydraulic mobile robots. A special User Group has been formed.

A second successful conference, on "The Telephone and Your Computer", (Prestel and networks) was organised at Easter by the ACC Chairman, Peter Whittle. This also promises to spawn a special user Group.

Other ACC activities include a technical enquiry service and hardware, software and literature libraries.

Individual membership costs £4.50 for the year, including the six copies of the Newsletter. Facilities are available to negotiate a group membership for a whole club — which has already been taken up by the North London Hobby Computer Club. Their members all receive a copy of *ACCumulator* — to which the Club adds its own newsletter. This reduces the workload of busy club officers, and saves duplication of effort.

For further information, contact Rupert Steele (Membership and technical enquiries) St John's College, Oxford, OX1 3JP or Veron Gifford (Liaison and Clubs) 111 Selhurst Road, London, SE25 6LH. Tel: 01-653 3207.

# Computer

Enter the world of sound technology with this simple program which allows you to compose music on a piano-like keyboard

With Computer Concerto you can compose your own music. Using the sound generating facility of the Vic-20 the program plays notes at the touch of a key.

It displays a representation of a section of the piano Keyboard on the tv screen and produces one-and-a-half octaves of notes, including the sharps and flats.

When a selected key is depressed the sound is produced and the particular note chosen is indicated on the display by an asterisk below the relevant piano key.

To get the note C, press the C-key and so on. The control key gives the sharps and flats and the shift key gives the upper octave.

So, for example, when pressing B, the shift and control keys together make B# in the upper register.

## The program

The program itself is quite simple and is most easily understood if it is considered in five parts.

1 Lines 100 to 135 print the keyboard display showing the tones and sem-tones CDEFGABCDEF.

2 Lines 200 to 245 are the data for producing the notes. N gives the frequency data, K gives the key data

and KS indicates the shift and control key data.

3 Lines 300 to 335 look at the keyboard and compare the values which have been entered with the data in Lines 205 to 225.

4 Lines 300 and 305 look at the character keys and the shift and control keys on the keyboard.

5 Lines 315 and 330 search through the data for the matching values.

When the correct data is located the program jumps out of the search loop to Line 400. Lines 400 to 425 then produce the desired note, N, selected from the data arrays, originally keyed-in as KI and KS.

The Vic-20 has three audio oscillators on board and the program pokes a combination of two of them, 36874 and 36875, in Lines 400 and 405.

In Line 415 the amplitude control, 36878, is poked and the loop in Line 410 then produces a decaying amplitude. The combination of locations 36874, 36875 and 36878 produces a warm tone with some persistence, simulating the sound of a piano.

Lines 350 to 395 display an asterisk on the screen below the pitch played, so that you can see as well as hear the note.

This program is just a start to making music on the Vic-20. It would be quite easy to adapt Computer Concerto in order to vary the lengths of the notes played and to store and retrieve them, making it possible to compose tunes and play them back. Such an adaptation would be well worth a try.


Whether you are a budding Bach or the next Haircut 100, there should be no stopping you!

Specially written for  
*Popular Computing Weekly*  
by  
**Nick Hampshire**




# Concerto

```
10 SP$="[21SPACES]"
100 PRINT "[CLR,HOME,3CD]"
105 PRINT " C D E F G A B C D E F"
110 FOR Q=1 TO 5
115 PRINT "|  2  2  2  2 |  2  2  2  2  2  2 |  2  2  2  2 |"
120 NEXT Q
125 FOR Q=1 TO 5
130 PRINT "| | | | | | | | |"
135 NEXT Q
200 DIM N(21),K(21),KS(21)
205 DATA 191,34,0,195,34,2,198,18,0,201,18,2
210 DATA 204,49,0,0,0,0,207,42,0,210,42,2,213,19,0
215 DATA 215,19,2,217,17,0,219,17,2,221,35,0,0,0,0
220 DATA 223,34,1,225,34,3,227,18,1,228,18,3
225 DATA 230,49,1,0,0,0,231,42,1
230 FOR X=0 TO 20
235 READ A,B,C
240 N(X)=A:K(X)=B:KS(X)=C
245 NEXT X
300 KI=PEEK(203)
305 KS=PEEK(653)
310 FOR X=0 TO 20
315 IF KI=K(X) THEN 330
320 NEXT X
325 GOTO 300
330 IF KS=KS(X) THEN 350
335 GOTO 320
350 PRINT "[HOME,17CD]";
355 PRINT SP$
395 PRINT "[CU] ";RIGHT$(SP$,X);"*";SP$
400 POKE 36874,N(X)
405 POKE 36875,N(X)
410 FOR Z=15 TO 0 STEP -1
415 POKE 36878,Z
420 FOR W=1 TO 20:NEXT W
425 NEXT Z
430 GOTO 300
```



# Reviews

## software



### Packman

Available from any Commodore dealer.  
Price £8.95.

One of last year's successes in the arcade game world was *Packman*, a game in which you had to control a little monster roaming around a maze gobbling up 'dots' (and thus gaining points) as he went around.

Lives were lost by being eaten by one of the four men rushing around after you: three lives was the usual limit, with a bonus life at some point in the scoring.

Other features included fruit, which would appear from time to time, and additional points were to be had by eating these delicacies.

There were always four special dots in the corners of the maze. Eating these changed the men chasing you from hunters into runners, and you could then eat them as a further method of scoring points.

The reason for mentioning all of this is quite simple: the success of any reproduction of an arcade game for a small micro depends on how faithful that reproduction is.

*Packman*, by Hi-Tech, comes on cassette, and fits quite happily into the standard Vic-20. The rules are not explained anywhere: presumably they assume that you know the game from your local pub.

All they do tell you is how to control your monster, which proves to be somewhat difficult, as the four keys enabling you to move up, down, left, and right are all next to each other, and it's very easy to get into quite a tangle.

The maze on which the game is enacted does not use the whole Vic screen, although the program does use the now common practice of filling the whole of your tv screen. Use of graphics and sound is not very good, and the game as a whole is quite slow to respond to your commands.

#### Summary

Some of the features of the original arcade game are missing so all in all it's not one of the best games currently available. **PG**

### Cassette AB

Cadsoft, 24 St James' Street,  
Cheltenham, Glos.  
Price £5.20.

Do you like the stirring informative title of this cassette? It is in fact a double feature, containing the five programs each from Cassettes A and B (£3 each). Now you know. Know too that Cadsoft also sell cassette Z (four 16K programs for £3) and listings of most of their products.

The author(s) of the Cassette AB programs show a commendable ingenuity in coping with 1K restrictions in pure Basic. None of the programs are novel, but they all work and are fairly good implementations of standard ideas.


*Guess the Word* is 'similar to hangman with no graphics'. Well, at least you're warned — I've seen hangman routines without graphics and no warning of it! The trick here is that the user enters the words to guess from a printed list where they are in code — so the computer knows what they are, but you don't.

There's also *Towers of Brahma* (with five rings to move); versions of a *Mastermind*, *Simon*, *Flyswat*, *Lander*, *Duckshoot* and *Number Square* (3 x 3); and an impressive little *Fruit Machine*.

This is all very pedestrian, then — but I guess someone has to make 1K ZX81 versions of the standard games. Cadsoft's are fairly cheap, load without problems, and come with good documentation.

#### Summary

A fair-value compilation of nice BASIC versions of standard games. **KJ**



### Vicmen

Available from any Commodore dealer.  
Price £8.95.

*Vicmen*, by Bug Byte, is a significant improvement. Again available on cassette for the standard Vic, it uses the whole of the tv screen for the game, and envelops

all of the features in the game we know and love. It is very well written and is quick to respond to your requests.

Two complaints mar what should have been a very good program. As in the Hi-Tech game, the keys for moving your man are next to each other, making life awkward to say the least. Secondly, the background music (there is no difference in noises when different events take place in the game) is enough to send you looking for the nearest cliff to jump off: depressing is not the word.

#### Summary

If you've got nimble fingers, and a volume control on your set, you're in for an enjoyable time with this particular cassette. **PG**

### Mission Of The Deep

Macronics, 26 Spiers Close, Knowle,  
Solihull, West Midlands.  
Price £5.00.

This is one of those awful 'blind graphics adventure' games — I have no other name for the genre. As with all adventures you don't know where you are, what you're doing, or how to do it.

In this case the maze is hidden until the end and the fierce crabs jump out at you with little warning and little chance of escape. It's addictive for millionaires, the unemployed and other persons of leisure!

The program starts rather strangely, with LOADED — PRESS ANY KEY TO RUN. (I'm not sure what happens if it doesn't load). After that you're straight into deep black water: on your own.

The accompanying notes do provide some sort of guidance to the three levels of play. I've no doubt that some real addicts would say that these notes are disgracefully over-detailed, but in reality they give just about adequate help for those new to such experiences. They tell you how to cheat for instance — most unwise.

It's not for me to tell you how to get to the bottom — of the program I mean. So that doesn't leave much for me to tell you.

Personally I prefer Macronics' animated graphics games, some of which are superb. All the same this is as good an example of 'blind graphics adventure' as any I've seen, and while the graphics don't come up to Atari standards, they'll do.

*Mission Of The Deep* is a Basic program taking up some 13K of RAM. It loads easily and is appealing to folk of all ages.

#### Summary

An excellent ZX81 example of the blind graphics adventure genre of computer game. No problem if you're into such things. **KJ**

# Reviews

## hardware

### Vic 1515 Printer

Available from Commodore dealers.  
Price £230.

Why Commodore should make the price of Vic peripherals such as the 1515 printer or the 1540 disc drive considerably greater (currently!) than the price of the Vic itself is a mystery best known to themselves. However, we're stuck with it, so what do you get for your £230 when you buy the Vic printer?

The printer connects up to the serial port on the Vic, and thus, as with the Vic disc drive, can be daisy chained to other serial bus devices.

This is not quite so mad as it might seem, as the printer has a switch on the front enabling you to change the device number to be either 4 or 5. Consequently two different printers can have two different device numbers and be used for varying functions.

The switch also allows you to run the printer through a self-diagnostic test, which simply prints out all the possible characters available from the Vic keyboard.

It is a 30 character per second unidirectional printer, using a five x seven dot matrix. Capable of printing out all the Vic graphics set, you can also have individual dot addressable graphics, although this does tend to wear out the print head rather rapidly.

Maximum paper size is 80 columns, but unfortunately it takes non-standard size tractor feed stationery, which is quite difficult to get hold of — surprising in a peripheral for a machine aimed at the consumer market.

The quality of the output when in upper case mode is quite good, but switching into lower case produces some odd results.

The letter p for instance (there are others) looks very much the same in both upper and lower case, thus making readability somewhat difficult. As the main function of a printer is to reproduce what would otherwise appear on the screen, this is something that Commodore ought to be looking at.

There is a routine in the manual to dump the contents of the screen on to the printer: a nice touch.

There are 12 control codes available on the printer, and two secondary addresses for selecting whether you want to be in cursor up mode or cursor down mode. These enable you to print in both upper and lower case at the same time.

The control codes give you access to such features as double width characters, reverse field, user definable characters and so on.

With a print speed of only 30 characters-

per-second listing out a long program can become particularly tedious. It is also an exceedingly noisy printer. If you've got a long listing to do, go outside, make yourself a cup of coffee and let the printer get on with it.

#### Summary

It is an expensive, noisy, slow printer but with fairly clear output. It does have some redeeming features like the character coding. However, as it's just about the only printer on the market at the moment you haven't got a lot of choice!

PG

### ZX81 QWERTY Keyboard

Computer Keyboards, Glendale Park,  
Fernbank Road, Ascot, Berks. Tel:  
03447-5661.

Price £28.95; assembled version £31.04;  
case £15.

This is not an ordinary ZX81 keyboard with 40 push button keys, but a professional QWERTY keyboard converted to work with the ZX81.

The QWERTY keyboard is the type seen on a typewriter and this version for the ZX81 also includes a space bar. The keys are also laid out in the stepped fashion of a typewriter, making the feel of the keys easier to the touch typist.

The keys are the same as those found on many other computer terminals and they have a reputation for long life. The key tops are covered with clear plastic covers under which can be placed the Sinclair signs and symbols.

There are six extra keys (three on each side) which can be wired up as user definable keys like the BBC machine if it has a port attached.

The keyboard size is 10" x 4½" x 2" and can either be mounted as supplied (with rubber feet) or in an aluminium case. The case can be used to house the ZX81's printed circuit board and also provided is a metal strap to clamp the Sinclair 16K RAM pack to the case.

Connection to the ZX81 is done via a set of plastic strips which plug into sockets on the keyboard. This means that there is no soldering required if you buy the assembled version.

The improvement in speed is usually in the range of 50 per cent depending on your typing speed. There is a limit on the speed at which keyboard entries can be made of five characters a second, which is set by the ZX81. If you try to beat it then some entries will not register in the computer.

This keyboard is one of the best I have seen as it allows people who have used a typewriter keyboard before to raise their inputting enormously. It can also speed up

games to make it easier to beat the computer!

The kit is fairly easy to construct as all keys are in one big block and there is no way you can get them to fit in the wrong way round. The ZX81, when mounted inside the case, stabilises the RAM pack beautifully as the pcb is firmly held in the case. SA

### Fun with Microcomputers

By Donald D Spencer.

Reward Books, 128 pages paperback  
£7.45.

This is the sort of book that must sell well to the casual bookshop browser — A4 pages littered with cartoons, plenty of program listings and a colourful cover. The price though, may be rather off-putting (yet this is \$9.95 in America, where it comes from, which typefies the mark-up on books imported across the Atlantic).

When that casual purchaser unwraps the package in the comfort of his/her own home, however, second impressions are likely to be less appealing.

The colourful cover shouts, 'Painless programming for kids and adults — no experience required! The games, puzzles and problems in this book introduce you to programming with BASIC quickly'.

There are two ways to learn programming — with understanding and without it. Both may be painful or painless, fun or drag. In essence, this book, a revamped issue of one called *Fun With Computers And BASIC* (1977) does not go too much for understanding, nor is using it a festival of fun.

Spencer starts off with a few chapters of theory. His language is casual but not straightforward. His facts are not all beyond dispute: For example: A semiconductor is an extremely small electronic component such as a transistor or a diode. These components act as on-off switches.

Then there is an introduction to BASIC programming — in eighteen pages. Not bad, but, as I say, not concerned overly with understanding.

The rest of the material is listings and programming tasks. There are 62 of these, a few being novel. Few listings take up more than about a page; they are in non-graphics terminal-style Basic and tend to be mathematically-biased.

I wouldn't recommend anyone to buy this book. All the same you may get some program ideas from it — induce your local library to get a copy.

#### Summary

This little book does not fulfil its initial promise. It is rather superficial and out-of-date but contains a few useful listings. KJ

 **commodore**

# COMPUTING

Own or use a Pet or a Vic? Fed up with being ignored by all the traditional monthly magazines? Fed up with listings which are too simple or simply do not work?

You need Commodore computing, the new monthly magazine. It is published by Nick Hampshire, author of *The Pet Revealed*, *Pet Graphics*, *A Library Subroutines* and *the Vic Revealed*. Each issue is packed with advanced advice on how to make the most of your computer, whether you use a Pet or a Vic, and whatever your application. Software, hardware, machine code, games, business use — it is all covered in every issue.

If you want to learn more about your computer, take out a subscription to *Commodore Computing*. It is the only way to get it, and get it straight.

**Send £12.50 for a subscription  
for 1 year (10 issues) to:**

**COMMODORE COMPUTING, MAGSUB,  
OAKFIELD HOUSE, PERRYMOUNT ROAD,  
HAYWARDS HEATH, SUSSEX RH16 3DH**

# Open Forum

*Open Forum is for you to publish your programs and ideas.*

*It is important that your programs are bug free before you send them in. We cannot test all of them.*

*Contributions should be sent to: Popular Computing Weekly, Hobhouse Court,  
19 Whitcomb Street, London WC2H 7HF.*

## Print using routine

on ZX81

The ZX81 Basic lacks a PRINT USING instruction. The PRINT USING instruction is particularly useful for tabulating a list of mixed alpha-numerical data, when the numbers have to have the decimal points lined up in columns. It is also useful to be able to specify the number of decimal places to be printed, regardless of the precision of the number.

The listing shown in figure 1 contains a PRINT USING routine in lines 7000 to 9570.

Lines 30 to 470 explain how to use the routine, and lines 1000 to 1400 contain a demonstration program to show the routine in use. Figure 2 shows the output from a run of this program — the data is quite arbitrary.

In order to use the PRINT USING routine, you must first specify the format required.

This is done by setting up Z\$ to the desired format. Z\$ represents a line across the screen and thus should not normally be more than 32 characters in length. "\$" is used to indicate where literal strings are to be printed and "\*" is used to indicate where numbers are required.

The position of the decimal point (if any) is indicated by a ".". The number of places of decimals to be printed is controlled by the number of "" after the ".". For example values from -8.99 to 99.99 are allowed by \*\*. Outside this range (ie the range specified by the number of \* in Z\$) error 6 will result.

Any characters in Z\$ other than \$ or \* will be printed as they stand in the positions occupied in Z\$.

Secondly, you must assign the data to be printed to the string Y\$. Each item of data must match that expected in Z\$ and should be separated by a comma (.). Numbers or numerical variables should be assigned using the STR\$ function and all data should

## YOUR PROGRAM COULD WIN A PRIZE!

Each week the editor goes through all the programs that you send to Open Forum in order to find the Program of the Week.

The author of that program will qualify for DOUBLE the usual fee we pay for published programs (the usual fee is £10).

Then at the end of the month the four best programs of the week go forward to our amazing Program of the Month contest, for which there is a STAR prize.

This month the star prize is a super ZX printer, worth £59.95!

And at the end of the year, all the best Programs of the Month will be entered in the super colossal competition, Program of the Year.

So send in your program today!

Programs which are most likely to be considered for the Star Prize will be computer printed and accompanied by a cassette.

The programs will be well documented, the documentation being typed with a double spacing between each line.

The documentation should start with a general description of the program and then give some detail of how the program has been constructed and of its special features.

Listings taken from a ZX Printer should be cut into convenient lengths and stuck down on to white paper.

Please enclose a self-addressed envelope.

be linked together using the "+". Y\$ must end with a comma.

For an example, see lines 1310 and 1340 and 1340-1360 in figure 1.

Lastly, to print a line of data, call the routine at line 7030, ie GOSUB 7030.

The program routine uses the following variables:

**FNO** — factor to generate the required number of decimal places.

**DECPNT** — points to the decimal point in X\$.

**DP** — points to the decimal point in Z\$.

**PLACES** — number of decimal places to be printed.

**X\$** a string to hold number to be printed.

**Y\$** — a string to hold data.

**Z\$** — a string specifying the format:  
\$ for literal.

\* for numbers.

. for decimal point.

anything else is printed unchanged.

**Lines 7030-7070** scan Z\$, characted by characted for \$ or \*.

**Line 7040** detects the start of a string. Strings are 'left justified'. The routine at line 8000 to 8270 is called to print the string, padding out or truncating as necessary to the exact number of \$ or Z\$.

**Line 7050** detects where the start of a number is to be printed. The routine at lines 9000-9570 is called to print the number. If the width of the field Z\$ is inadequate, error 6 will result.

**Line 7060** will print the character in Z\$ if it is neither a \$ nor a \*.

**Line 7080** will cause the next call to the routine to start a fresh line.

## String handling routine

**Line 8030** sets Y to point to the first character of Y\$.

**Lines 8040-8050** print a character and increments Y to point to the next character.

**Lines 8060-8080** check whether another character is to be printed (\$ in Z\$). If the end of Z\$ is reached, or if there is no \$, printing will stop and control will pass to line 8140 to truncate the string.

**Line 8090** checks whether the string in Y\$ is shorter than the space allowed, and if so jumps to line 8170 to 'pad' out the field with spaces.

## Truncate

**Lines 8140-8160** scan for the end of the string in Y\$ (indicated by the .). Thereby truncating the string.

# Open Forum

**Line 8170** discards from Y\$ the item of data, so that the next item of data is at the start of Y\$.

## Pad out

**Line 8220** discards from Y\$ the item of data, so that the next item of data is at the start of Y\$.

**Lines 8230-8260** pad out the field with spaces until Z\$ runs out of \$ or the end of Z\$ is reached.

## Number handling routine.

**Line 9030** sets Y to point to the first character of Y\$.

**Line 9040** sets Y\$ to a NULL string.

**Line 9050** checks whether the first character is a "." (for value less than 1).

**Lines 9060-9090** assign X\$ to the number up to the decimal point.

**Line 9100** saves the position of the decimal point.

**Lines 9110-9140** assign the remainder of the number.

**Line 9150** discards from Y\$ the data item, so that the next item to be processed is at the start of Y\$.

**Lines 9160-9200** find the position of the decimal point in Z\$.

**Line 9210** checks whether the field is large enough for printing.

**Lines 9220-23 and 9540-9570** find the number of decimal places.

**Line 9240** calculates the multiplying factor FNO.

**Line 9250** prints the number in the required position ie aligns the decimal points and prints the required number of decimal places.

**Line 9260** sets Z to point to the next character in Z\$.

## Graphics

on BBC Micro

Here are four programs to show the BBC Micro graphics in operation. The first one selects elements of the string A\$ (defined in line 50) to produce a balanced, evolving pattern.

The second program, *Coloured Lace*, is based on the first one, but it uses a string of full stops and spaces, producing quite a different result.

The third program, *Tesseract*, based on a program by Alastair Gourlay, uses the string defined in line 70 in an unexpected way to produce more balanced patterns. From time to

## Print using routine

By Roy Eastwood

```

10 REM PRINT USING ROUTINE BY
20 REM ROY EASTWOOD. MARCH 19
82
30 REM
40 REM TO USE THE ROUTINE, SET
50 REM UP THE STRING Z$
60 REM TO THE DESIRED
70 REM FORMAT. USE $ FOR
80 REM LITERAL STRINGS, AND *
90 REM FOR NUMBERS. USE A "...
100 REM TO INDICATE WHERE THE
110 REM DECIMAL POINT IS TO BE
120 REM PRINTED. THE NUMBER
130 REM OF PLACES PRINTED AFTER
140 REM THE DECIMAL POINT WILL
150 REM BE LIMITED BY THE
160 REM NUMBER OF * IN Z$.
170 REM FOR EXAMPLE: **. **
180 REM WILL GIVE 2 DECIMAL
190 REM PLACES AND WILL CATER
200 REM FOR VALUES UP TO
210 REM 99.99.
220 REM
230 REM THE DATA SHOULD BE
240 REM ASSIGNED TO A STRING
250 REM Y$. BOTH LITERAL AND
260 REM NUMERICAL DATA SHOULD
270 REM BE ASSIGNED AND EACH
280 REM DATA ITEM SEPARATED BY
290 REM A COMMA. Y$ MUST END
300 REM WITH A COMMA. USE THE
310 REM STR$ FOR NUMERICAL DATA
320 REM AND CONCATENATE ALL
330 REM ITEMS USING THE "+".
340 REM
350 REM FOR EXAMPLE: TO PRINT
360 REM A$, A AND THE CONSTANT
370 REM 87.4, USE:
380 REM LET Y$=A$+","+STR$ A$
390 REM STR$ 87.4+", "
400 REM
410 REM FOLLOWED BY:
420 REM GOSUB 7030
430 REM
440 REM THERE FOLLOWS A SAMPLE
450 REM RUN. THE ROUTINE PROPER
460 REM STARTS AT LINE 7000.
470 REM
480 REM SAMPLE RUN
490 REM
500 DIM A$(20,10)
510 DIM B(20)
520 DIM B(20)
530 LET A$(1)="ASPARAGUS"
540 LET A$(2)="ARTICHOKE"
550 LET A$(3)="BREAD"
560 LET A$(4)="BUTTER"
570 LET A$(5)="CHEESE"
580 LET A$(6)="CUCUMBER"
590 LET A$(7)="EGGS"
600 LET A$(8)="FISH"
610 LET A$(9)="GHERKINS"
620 LET A$(10)="HARICOT"
630 LET A$(11)="ICE CREAM"
640 LET A$(12)="JAM"
650 LET A$(13)="LETTUCE"
660 LET A$(14)="MUSTARD"
670 LET A$(15)="NUTS"
680 LET A$(16)="ORANGES"
690 LET A$(17)="PORK"
700 LET A$(18)="QUINCES"
710 LET A$(19)="RABBIT"
720 LET A$(20)="SALT"
730 LET Z$="$$$$"
740 LET Y$="ITEM,PRICE,QTY,COST"
750 GOSUB 7030
760 LET Z$="$$$$$$$$$$$$$... *.*"
770 ***
780 PRINT
790 FOR N=1 TO 20,
800 LET Y$=A$(N)+", "
810 LET A(N)=INT (AND*300)/100
820 LET B(N)=INT (AND*1000)
830 LET Y$=Y$+STR$ A(N)+", "
840 LET Y$=Y$+STR$ B(N)+", "
850 LET Y$=Y$+STR$ (INT ((A(N)+
860 B(N)+100)/100)+", "
870 GOSUB 7030
880 PRINT N
890 STOP
900 REM
910 REM *****
920 REM PRINT USING ROUTINE
930 REM *****
940 FOR Z=1 TO LEN Z$
950 IF Z$(Z)="*" THEN GOSUB 803
960
970 IF Z$(Z)="" THEN GOSUB 903
980
990 IF Z$(Z)(">") AND Z$(Z)("<")
1000 THEN PRINT Z$(Z);
1010 NEXT Z
1020 PRINT
1030 RETURN
1040 REM *****
1050 REM *****
1060 REM *****
1070 REM *****
1080 REM *****
1090 LET Y=1
1100 PRINT Y$(Y);
1110 LET Y=Y+1
1120 IF Z)=LEN Z$ THEN GOTO 8140
1130 LET Z=Z+1
1140 IF Z$(Z)(">") THEN GOTO 814
1150
1160 IF Y$(Y)="" THEN GOTO 8220
1170 GOTO 8040
1180 REM *****
1190 REM *****
1200 REM *****
1210 REM *****
1220 REM *****
1230 REM *****
1240 REM *****
1250 REM *****
1260 REM *****
1270 REM *****
1280 REM *****
1290 REM *****
1300 REM *****
1310 REM *****
1320 REM *****
1330 REM *****
1340 REM *****
1350 REM *****
1360 REM *****
1370 REM *****
1380 REM *****
1390 REM *****
1400 REM *****
1410 REM *****
1420 REM *****
1430 REM *****
1440 REM *****
1450 REM *****
1460 REM *****
1470 REM *****
1480 REM *****
1490 REM *****
1500 REM *****
1510 REM *****
1520 REM *****
1530 REM *****
1540 REM *****
1550 REM *****
1560 REM *****
1570 REM *****
1580 REM *****
1590 REM *****
1600 REM *****
1610 REM *****
1620 REM *****
1630 REM *****
1640 REM *****
1650 REM *****
1660 REM *****
1670 REM *****
1680 REM *****
1690 REM *****
1700 REM *****
1710 REM *****
1720 REM *****
1730 REM *****
1740 REM *****
1750 REM *****
1760 REM *****
1770 REM *****
1780 REM *****
1790 REM *****
1800 REM *****
1810 REM *****
1820 REM *****
1830 REM *****
1840 REM *****
1850 REM *****
1860 REM *****
1870 REM *****
1880 REM *****
1890 REM *****
1900 REM *****
1910 REM *****
1920 REM *****
1930 REM *****
1940 REM *****
1950 REM *****
1960 REM *****
1970 REM *****
1980 REM *****
1990 REM *****
2000 REM *****
2010 REM *****
2020 REM *****
2030 REM *****
2040 REM *****
2050 REM *****
2060 REM *****
2070 REM *****
2080 REM *****
2090 REM *****
2100 REM *****
2110 REM *****
2120 REM *****
2130 REM *****
2140 REM *****
2150 REM *****
2160 REM *****
2170 REM *****
2180 REM *****
2190 REM *****
2200 REM *****
2210 REM *****
2220 REM *****
2230 REM *****
2240 REM *****
2250 REM *****
2260 REM *****
2270 REM *****
2280 REM *****
2290 REM *****
2300 REM *****
2310 REM *****
2320 REM *****
2330 REM *****
2340 REM *****
2350 REM *****
2360 REM *****
2370 REM *****
2380 REM *****
2390 REM *****
2400 REM *****
2410 REM *****
2420 REM *****
2430 REM *****
2440 REM *****
2450 REM *****
2460 REM *****
2470 REM *****
2480 REM *****
2490 REM *****
2500 REM *****
2510 REM *****
2520 REM *****
2530 REM *****
2540 REM *****
2550 REM *****
2560 REM *****
2570 REM *****
2580 REM *****
2590 REM *****
2600 REM *****
2610 REM *****
2620 REM *****
2630 REM *****
2640 REM *****
2650 REM *****
2660 REM *****
2670 REM *****
2680 REM *****
2690 REM *****
2700 REM *****
2710 REM *****
2720 REM *****
2730 REM *****
2740 REM *****
2750 REM *****
2760 REM *****
2770 REM *****
2780 REM *****
2790 REM *****
2800 REM *****
2810 REM *****
2820 REM *****
2830 REM *****
2840 REM *****
2850 REM *****
2860 REM *****
2870 REM *****
2880 REM *****
2890 REM *****
2900 REM *****
2910 REM *****
2920 REM *****
2930 REM *****
2940 REM *****
2950 REM *****
2960 REM *****
2970 REM *****
2980 REM *****
2990 REM *****
3000 REM *****
3010 REM *****
3020 REM *****
3030 REM *****
3040 REM *****
3050 REM *****
3060 REM *****
3070 REM *****
3080 REM *****
3090 REM *****
3100 REM *****
3110 REM *****
3120 REM *****
3130 REM *****
3140 REM *****
3150 REM *****
3160 REM *****
3170 REM *****
3180 REM *****
3190 REM *****
3200 REM *****
3210 REM *****
3220 REM *****
3230 REM *****
3240 REM *****
3250 REM *****
3260 REM *****
3270 REM *****
3280 REM *****
3290 REM *****
3300 REM *****
3310 REM *****
3320 REM *****
3330 REM *****
3340 REM *****
3350 REM *****
3360 REM *****
3370 REM *****
3380 REM *****
3390 REM *****
3400 REM *****
3410 REM *****
3420 REM *****
3430 REM *****
3440 REM *****
3450 REM *****
3460 REM *****
3470 REM *****
3480 REM *****
3490 REM *****
3500 REM *****
3510 REM *****
3520 REM *****
3530 REM *****
3540 REM *****
3550 REM *****
3560 REM *****
3570 REM *****
3580 REM *****
3590 REM *****
3600 REM *****
3610 REM *****
3620 REM *****
3630 REM *****
3640 REM *****
3650 REM *****
3660 REM *****
3670 REM *****
3680 REM *****
3690 REM *****
3700 REM *****
3710 REM *****
3720 REM *****
3730 REM *****
3740 REM *****
3750 REM *****
3760 REM *****
3770 REM *****
3780 REM *****
3790 REM *****
3800 REM *****
3810 REM *****
3820 REM *****
3830 REM *****
3840 REM *****
3850 REM *****
3860 REM *****
3870 REM *****
3880 REM *****
3890 REM *****
3900 REM *****
3910 REM *****
3920 REM *****
3930 REM *****
3940 REM *****
3950 REM *****
3960 REM *****
3970 REM *****
3980 REM *****
3990 REM *****
4000 REM *****
4010 REM *****
4020 REM *****
4030 REM *****
4040 REM *****
4050 REM *****
4060 REM *****
4070 REM *****
4080 REM *****
4090 REM *****
4100 REM *****
4110 REM *****
4120 REM *****
4130 REM *****
4140 REM *****
4150 REM *****
4160 REM *****
4170 REM *****
4180 REM *****
4190 REM *****
4200 REM *****
4210 REM *****
4220 REM *****
4230 REM *****
4240 REM *****
4250 REM *****
4260 REM *****
4270 REM *****
4280 REM *****
4290 REM *****
4300 REM *****
4310 REM *****
4320 REM *****
4330 REM *****
4340 REM *****
4350 REM *****
4360 REM *****
4370 REM *****
4380 REM *****
4390 REM *****
4400 REM *****
4410 REM *****
4420 REM *****
4430 REM *****
4440 REM *****
4450 REM *****
4460 REM *****
4470 REM *****
4480 REM *****
4490 REM *****
4500 REM *****
4510 REM *****
4520 REM *****
4530 REM *****
4540 REM *****
4550 REM *****
4560 REM *****
4570 REM *****
4580 REM *****
4590 REM *****
4600 REM *****
4610 REM *****
4620 REM *****
4630 REM *****
4640 REM *****
4650 REM *****
4660 REM *****
4670 REM *****
4680 REM *****
4690 REM *****
4700 REM *****
4710 REM *****
4720 REM *****
4730 REM *****
4740 REM *****
4750 REM *****
4760 REM *****
4770 REM *****
4780 REM *****
4790 REM *****
4800 REM *****
4810 REM *****
4820 REM *****
4830 REM *****
4840 REM *****
4850 REM *****
4860 REM *****
4870 REM *****
4880 REM *****
4890 REM *****
4900 REM *****
4910 REM *****
4920 REM *****
4930 REM *****
4940 REM *****
4950 REM *****
4960 REM *****
4970 REM *****
4980 REM *****
4990 REM *****
5000 REM *****
5010 REM *****
5020 REM *****
5030 REM *****
5040 REM *****
5050 REM *****
5060 REM *****
5070 REM *****
5080 REM *****
5090 REM *****
5100 REM *****
5110 REM *****
5120 REM *****
5130 REM *****
5140 REM *****
5150 REM *****
5160 REM *****
5170 REM *****
5180 REM *****
5190 REM *****
5200 REM *****
5210 REM *****
5220 REM *****
5230 REM *****
5240 REM *****
5250 REM *****
5260 REM *****
5270 REM *****
5280 REM *****
5290 REM *****
5300 REM *****
5310 REM *****
5320 REM *****
5330 REM *****
5340 REM *****
5350 REM *****
5360 REM *****
5370 REM *****
5380 REM *****
5390 REM *****
5400 REM *****
5410 REM *****
5420 REM *****
5430 REM *****
5440 REM *****
5450 REM *****
5460 REM *****
5470 REM *****
5480 REM *****
5490 REM *****
5500 REM *****
5510 REM *****
5520 REM *****
5530 REM *****
5540 REM *****
5550 REM *****
5560 REM *****
5570 REM *****
5580 REM *****
5590 REM *****
5600 REM *****
5610 REM *****
5620 REM *****
5630 REM *****
5640 REM *****
5650 REM *****
5660 REM *****
5670 REM *****
5680 REM *****
5690 REM *****
5700 REM *****
5710 REM *****
5720 REM *****
5730 REM *****
5740 REM *****
5750 REM *****
5760 REM *****
5770 REM *****
5780 REM *****
5790 REM *****
5800 REM *****
5810 REM *****
5820 REM *****
5830 REM *****
5840 REM *****
5850 REM *****
5860 REM *****
5870 REM *****
5880 REM *****
5890 REM *****
5900 REM *****
5910 REM *****
5920 REM *****
5930 REM *****
5940 REM *****
5950 REM *****
5960 REM *****
5970 REM *****
5980 REM *****
5990 REM *****
6000 REM *****
6010 REM *****
6020 REM *****
6030 REM *****
6040 REM *****
6050 REM *****
6060 REM *****
6070 REM *****
6080 REM *****
6090 REM *****
6100 REM *****
6110 REM *****
6120 REM *****
6130 REM *****
6140 REM *****
6150 REM *****
6160 REM *****
6170 REM *****
6180 REM *****
6190 REM *****
6200 REM *****
6210 REM *****
6220 REM *****
6230 REM *****
6240 REM *****
6250 REM *****
6260 REM *****
6270 REM *****
6280 REM *****
6290 REM *****
6300 REM *****
6310 REM *****
6320 REM *****
6330 REM *****
6340 REM *****
6350 REM *****
6360 REM *****
6370 REM *****
6380 REM *****
6390 REM *****
6400 REM *****
6410 REM *****
6420 REM *****
6430 REM *****
6440 REM *****
6450 REM *****
6460 REM *****
6470 REM *****
6480 REM *****
6490 REM *****
6500 REM *****
6510 REM *****
6520 REM *****
6530 REM *****
6540 REM *****
6550 REM *****
6560 REM *****
6570 REM *****
6580 REM *****
6590 REM *****
6600 REM *****
6610 REM *****
6620 REM *****
6630 REM *****
6640 REM *****
6650 REM *****
6660 REM *****
6670 REM *****
6680 REM *****
6690 REM *****
6700 REM *****
6710 REM *****
6720 REM *****
6730 REM *****
6740 REM *****
6750 REM *****
6760 REM *****
6770 REM *****
6780 REM *****
6790 REM *****
6800 REM *****
6810 REM *****
6820 REM *****
6830 REM *****
6840 REM *****
6850 REM *****
6860 REM *****
6870 REM *****
6880 REM *****
6890 REM *****
6900 REM *****
6910 REM *****
6920 REM *****
6930 REM *****
6940 REM *****
6950 REM *****
6960 REM *****
6970 REM *****
6980 REM *****
6990 REM *****
7000 REM *****
7010 REM *****
7020 REM *****
7030 REM *****
7040 REM *****
7050 REM *****
7060 REM *****
7070 REM *****
7080 REM *****
7090 REM *****
7100 REM *****
7110 REM *****
7120 REM *****
7130 REM *****
7140 REM *****
7150 REM *****
7160 REM *****
7170 REM *****
7180 REM *****
7190 REM *****
7200 REM *****
7210 REM *****
7220 REM *****
7230 REM *****
7240 REM *****
7250 REM *****
7260 REM *****
7270 REM *****
7280 REM *****
7290 REM *****
7300 REM *****
7310 REM *****
7320 REM *****
7330 REM *****
7340 REM *****
7350 REM *****
7360 REM *****
7370 REM *****
7380 REM *****
7390 REM *****
7400 REM *****
7410 REM *****
7420 REM *****
7430 REM *****
7440 REM *****
7450 REM *****
7460 REM *****
7470 REM *****
7480 REM *****
7490 REM *****
7500 REM *****
7510 REM *****
7520 REM *****
7530 REM *****
7540 REM *****
7550 REM *****
7560 REM *****
7570 REM *****
7580 REM *****
7590 REM *****
7600 REM *****
7610 REM *****
7620 REM *****
7630 REM *****
7640 REM *****
7650 REM *****
7660 REM *****
7670 REM *****
7680 REM *****
7690 REM *****
7700 REM *****
7710 REM *****
7720 REM *****
7730 REM *****
7740 REM *****
7750 REM *****
7760 REM *****
7770 REM *****
7780 REM *****
7790 REM *****
7800 REM *****
7810 REM *****
7820 REM *****
7830 REM *****
7840 REM *****
7850 REM *****
7860 REM *****
7870 REM *****
7880 REM *****
7890 REM *****
7900 REM *****
7910 REM *****
7920 REM *****
7930 REM *****
7940 REM *****
7950 REM *****
7960 REM *****
7970 REM *****
7980 REM *****
7990 REM *****
8000 REM *****
8010 REM *****
8020 REM *****
8030 REM *****
8040 REM *****
8050 REM *****
8060 REM *****
8070 REM *****
8080 REM *****
8090 REM *****
8100 REM *****
8110 REM *****
8120 REM *****
8130 REM *****
8140 REM *****
8150 REM *****
8160 REM *****
8170 REM *****
8180 REM *****
8190 REM *****
8200 REM *****
8210 REM *****
8220 REM *****
8230 REM *****
8240 REM *****
8250 REM *****
8260 REM *****
8270 REM *****
8280 REM *****
8290 REM *****
8300 REM *****
8310 REM *****
8320 REM *****
8330 REM *****
8340 REM *****
8350 REM *****
8360 REM *****
8370 REM *****
8380 REM *****
8390 REM *****
8400 REM *****
8410 REM *****
8420 REM *****
8430 REM *****
8440 REM *****
8450 REM *****
8460 REM *****
8470 REM *****
8480 REM *****
8490 REM *****
8500 REM *****
8510 REM *****
8520 REM *****
8530 REM *****
8540 REM *****
8550 REM *****
8560 REM *****
8570 REM *****
8580 REM *****
8590 REM *****
8600 REM *****
8610 REM *****
8620 REM *****
8630 REM *****
8640 REM *****
8650 REM *****
8660 REM *****
8670 REM *****
8680 REM *****
8690 REM *****
8700 REM *****
8710 REM *****
8720 REM *****
8730 REM *****
8740 REM *****
8750 REM *****
8760 REM *****
8770 REM *****
8780 REM *****
8790 REM *****
8800 REM *****
8810 REM *****
8820 REM *****
8830 REM *****
8840 REM *****
8850 REM *****
8860 REM *****
8870 REM *****
8880 REM *****
8890 REM *****
8900 REM *****
8910 REM *****
8920 REM *****
8930 REM *****
8940 REM *****
8950 REM *****
8960 REM *****
8970 REM *****
8980 REM *****
8990 REM *****
9000 REM *****
9010 REM *****
9020 REM *****
9030 REM *****
9040 REM *****
9050 REM *****
9060 REM *****
9070 REM *****
9080 REM *****
9090 REM *****
9100 REM *****
9110 REM *****
9120 REM *****
9130 REM *****
9140 REM *****
9150 REM *****
9160 REM *****
9170 REM *****
9180 REM *****
9190 REM *****
9200 REM *****
9210 REM *****
9220 REM *****
9230 REM *****
9240 REM *****
9250 REM *****
9260 REM *****
9270 REM *****
9280 REM *****
9290 REM *****
9300 REM *****
9310 REM *****
9320 REM *****
9330 REM *****
9340 REM *****
9350 REM *****
9360 REM *****
9370 REM *****
9380 REM *****
9390 REM *****
9400 REM *****
9410 REM *****
9420 REM *****
9430 REM *****
9440 REM *****
9450 REM *****
9460 REM *****
9470 REM *****
9480 REM *****
9490 REM *****
9500 REM *****
9510 REM *****
9520 REM *****
9530 REM *****
9540 REM *****
9550 REM *****
9560 REM *****
9570 REM *****
9580 REM *****
9590 REM *****
9600 REM *****
9610 REM *****
9620 REM *****
9630 REM *****
9640 REM *****
9650 REM *****
9660 REM *****
9670 REM *****
9680 REM *****
9690 REM *****
9700 REM *****
9710 REM *****
9720 REM *****
9730 REM *****
9740 REM *****
9750 REM *****
9760 REM *****
9770 REM *****
9780 REM *****
9790 REM *****
9800 REM *****
9810 REM *****
9820 REM *****
9830 REM *****
9840 REM *****
9850 REM *****
9860 REM *****
9870 REM *****
9880 REM *****
9890 REM *****
9900 REM *****
9910 REM *****
9920 REM *****
9930 REM *****
9940 REM *****
9950 REM *****
9960 REM *****
9970 REM *****
9980 REM *****
9990 REM *****
10000 REM *****

```

# Open Forum

## Graphics

By Tim Hartnell

```

10 REM PERPETUA
20 REM CHANGE A$ TO SUIT
30 MODE 7
40 VDU23;8202;0;0;0
50 A$="E$. . . *+. . .0."
60 C=38
70 D=22
80 REPEAT
90 B#=CHR$(128+RND(5))+MID$(A$,RND(15),1)
100 B=RND(22)
110 A=RND(38)
120 PRINTTAB(A,B);B#
130 PRINTTAB(C-A,B);B#
140 PRINTTAB(C-A,D-B);B#
150 PRINTTAB(A,D-B);B#
160 T=TIME
170 REPEAT UNTIL TIME-T>?
180 UNTIL FALSE

10 REM COLOURED LACE
12 REM BASED ON PERPETUA
20 REM CHANGE A$ TO SUIT
30 MODE 7
40 VDU23;8202;0;0;0
50 A$="....."
60 C=38
70 D=22
80 REPEAT
90 B#=CHR$(128+RND(5))+MID$(A$,RND(15),1)
100 B=RND(22)
110 A=RND(38)
120 PRINTTAB(A,B);B#
130 PRINTTAB(C-A,B);B#
140 PRINTTAB(C-A,D-B);B#
150 PRINTTAB(A,D-B);B#
160 T=TIME
170 REPEAT UNTIL TIME-T>?
180 UNTIL FALSE

10 REM**TESSERACT**
20 REM**ALASTAIR GOURI YX**
30 MODE7
40 VDU23;8202;0;0;0
50 P=11
60 CLS
70 B#=CHR$(128+RND(6))+CHR$(41+RND(2))
80 IF RND(10)<5 B#=""
90 X=RND(P)
100 Y=RND(P)
110 PRINTTAB(P+X,P+Y);B#
120 PRINTTAB(P+Y,P+X);B#
130 PRINTTAB(P-X,P+Y);B#
140 PRINTTAB(P+Y,P-X);B#
150 PRINTTAB(P-X,P-Y);B#
160 PRINTTAB(P-Y,P-X);B#
170 PRINTTAB(P+X,P-Y);B#
180 PRINTTAB(P-Y,P+X);B#
190 X=X+RND(1)+RND(1)-1
200 Y=Y+RND(1)+RND(1)-1
210 IFRND(10)<2 OR ABS X>P OR Y>P THEN?
220 SOUND3,-RND(15),RND(50)+200,RND(3)
230 SOUND1,-RND(15),RND(10)+20,RND(3)
240 IF RND(70)=50 CLS
250 GOTO70

```

time this program will clear the screen (see line 240) to start all over again.

The fourth program, *Solids*, is based on a routine which originally plotted an oval in Mode 4. The program chooses the centre point of the oval, and its height and width randomly, then plots the oval around this, using a random step size (see line 120) based on the number produced in line 110.

Lines 70 and 80 determine whether or not the plotted shape will be moved slightly up, down, left or right before being re-plotted.

The resultant shape, which varies every time you run the program, resembles a solid figure, which explains the title.

## An average peek

on ZX81

The ZX81 manual explains how to find what byte is at a given ROM address, and these values vary between 0 and 255. It is of interest to know what the average ROM byte value is, and what is the total numerical value of all the bytes, up to a given address.

This can be rapidly calculated by the following program (for 1K RAM). To avoid the program 'blowing up' at the address 0, the average peek value in the ROM is defined as:

$$\text{average} = \frac{\text{TOTAL bytes}}{\text{ROM address} + 1}$$

```

5 REM PEEK AVERAGING FOR ROM
10 PRINT "ADDRESS"; TAB 8; "BYTE"; TAB 14;
  "TOTAL"; TAB 20; "MEAN"
20 LET TOTAL = 0
30 FOR A = 0 TO 200 STEP 1
40 LET TOTAL = TOTAL + PEEK A
50 PRINT A; TAB 8; PEEK A; TAB 14; TOTAL;
  TAB 20; TOTAL/(A + 1) An Average Peek
60 NEXT A

```

By Roy H. S. Bluston

The results are displayed in four columns with the headings ADDRESS, BYTE, TOTAL and MEAN. By varying the upper limit on line 30, as many results as required can be displayed and also the STEP length can be varied as required.

It was found that for address numbers up to 200 the average byte value varies between 110 and 128. The program fits well inside the ZX81, 1K RAM and the running time will depend on the upper limit in line 30 and the STEP value.

# Open Forum

## Spacefighter

on Vic-20

As this program utilises user-defined graphics, it will only work with the unexpanded Vic. The main aim of the game is to destroy as many enemy fighter ships as possible in 100 seconds.

The enemy ships appear from the mother ship at the top of the screen. The player aligns the sights on an enemy target and fires.

The sights can be moved in all four directions and once you move the sight cursor it will continue to move until you release the key.

When the program is run, it first asks you whether you want instructions or not (Lines 12000 to 12240).

While you are reading the instructions the computer designs the hi-resolution characters and copies the alphabet into RAM.

When this has been completed the RAM character generator is activated by Line 35. After this is finished the computer draws the alien mother ship and fighters and Lines 85 to 2090 make the fighters move down the screen and also draws the sights.

Lines 4000 to 4030 carry out the firing sequence and also see if you have hit your target. If you hit your target head-on the computer plays a chaotic tune and awards you 10 points (Lines 8500 to 8700).

If you only strike the alien craft a glancing blow the computer only makes an explosion noise and awards you 5 points.

If you wish to use a joystick then you must adjust Lines 2010 to 2056.

## Flash counting

on ZX81

The object of this program is to train the user in 'flash counting' counting groups at a glance without breaking them down into single items.

The program displays a random number of black squares in the top half of the screen in a random pattern. After a few moments these are removed and the user is invited to estimate how many squares were displayed.

After each attempt the computer gives the correct number and after 10

## Spacefighter

By S Mahmood

```
1 POKE650,129
2 POKE36879,8:PRINT"J" POKE36878,15
3 GOTO 12000
10 P=7932
21 TI#="000000"
22 POKE 36879,8
30 C=7734 D2=1 C3=C+5 C4=C3+2
35 POKE 36869,255
41 PRINT"#####C+#####C+##"
42 FORI=1TO70
50 POKE 7724+INT(RND(1)*500),46
60 NEXT
85 D2=INT(RND(1)*4)+1
90 D=INT(RND(1)*3)+20
92 D1=INT(RND(1)*3)+20
93 D4=INT(RND(1)*3)+20
95 POKE 36877,220
100 POKEC,32:POKEC3,32:POKEC4,32
120 IF C+D>8180 THEN C=7734
121 IF C4+D4>8180 THEN C4=7734+4 D2=INT(RND(1)*4)+1
122 IF C3+D3>8180 THEN C3=7734 D2=INT(RND(1)*4)+1
130 C=C+D:C3=C3+D1 C4=C4+D4
140 POKE 30720+C,D2:POKEC,0:POKE30720+C3,D2:POKEC3,0:POKE30720+C4,1*POKEC4,0
2000 POKE P,198:POKEP+2,198:POKEP-21,221:POKEP+23,221
2002 POKE P,198:POKEP+2,198:POKEP-21,221:POKEP+23,221
2003 PRINT"#####SCORE"
2004 IF TI#="000100" THEN 15000
2005 FORE=1TO 25 NEXTE
2006 PRINT"#####SCORE"
2007 POKE36877,0:POKE36875,0:POKE36876,0
2010 GETO# :F=0
2011 IF O#="" THEN 2015
2012 POKE P,32:POKEP+2,32:POKEP-21,32:POKEP+23,32
2015 IF WR=2 THEN WR=0 GOTO6500
2020 IF O#="|" THEN F=22
2030 IF O#="|" THEN F=-22
2040 IF O#="." THEN F=-2
2050 IF O#="/" THEN F=2
2055 IF O#="|" THEN GOTO 4000
2057 IF F=0 THEN 2060
2058 POKE36876,200
2060 P=P+F
2070 IF P<7790 THEN P=P+22
2080 IF P>8094 THEN P=P-22
2081 R04=R04+1
2082 IF INT(R04/2)=R04/2 THEN POKE7175,129
2083 IF INT(R04/2)<>R04/2 THEN POKE7175,66
2090 GOTO 90
4000 K=P-2:L=P+4:M=P-65:N=67+P
4001 POKE 36877,P-K+200:POKE198,0
4002 IF N<4096+500 THEN P=32
4003 IF WR=2 THEN WR=0 GOTO6500
4004 IF K=P THEN GOTO2010
4005 POKE P,198:POKEP+2,198:POKEP-21,221:POKEP+23,221
4006 IF PEEK(K)=0 OR PEEK(M)=0 OR PEEK(N)=0 OR PEEK(N)=0 THEN WR=1:W4=W4+5
4008 IFPEEK(P+1)=0 THEN W4=W4+10:WR=2
4010 POKE -K,198:POKEL,198:POKEN,221:POKEM,221
```

# Open Forum

```

4012 IF NR=1 THEN NR=0:GOTO3000
4015 FOR I=1 TO 50: NEXT I
4018 POKE K:32:POKE L:32:POKE N:32:POKE M:32
4020 K=K+1:L=L+1:M=M+22:N=N+22
4022 GOTO 4002
3500 POKE36877:0
3550 FOR L2=1 TO 100:POKE36876:INT(RND(1)*125)+125
3600 FORM=1 TO 8: NEXT M
3700 NEXT L2
3800 POKE36876:0:POKE P+1:42
3900 POKE36877:220:POKE Y+15 TO 200:STEP 1:POKE36876:UY
3905 PRINT"8TIME":RIGHT#(TIF:3)
3906 FORM=1 TO 200: NEXT M:UY
3910 POKE36877:0:POKE36878:8
3920 REM
3955 POKE 198:0
3960 GOTO41
12000 POKE36879:219
12010 PRINT"███"
12030 PRINT"      █SPACEFIGHTER█"
12040 INPUT"██████INSTRUCTIONS" :OF
12050 IF OF="M" THEN 12050
12070 IF OF="H" THEN PRINT"██████████HERE WE GO " GOTO30000
12075 GOTO12010
12080 GOTO 12030
12090 PRINT"IN THIS GAME YOU MUST LOOK THROUGH THE CROSSHAIR FIRE AT COMING
12100 PRINT"INVASERS WHICH COME FROM THE MOTHER SHIP AT THE TOP OF THE "
12120 PRINT"SCREEN "
12130 PRINT"███ POINTS IF YOU HIT THEM FROM THE SIDE"
12140 PRINT"███ POINTS IF YOU HIT THEM DIRECTLY"
12145 PRINT"YOU HAVE 1000███ SEC:W.DS"
12150 PRINT"██████ANY KEY TO CONTINUE"
12160 GET OF:IF OF="" THEN 12160
12170 PRINT"███ SPACE FIGHTER███"
12180 PRINT"███THE CONTROLS ARE -"
12190 PRINT"███ KEY TO MOVE LEFT"
12200 PRINT"███ KEY TO MOVE RIGHT"
12220 PRINT"███F1 KEY TO MOVE UP"
12230 PRINT"███F3 KEY TO MOVE DOWN"
12240 PRINT"███F5 KEY TO FIRE███"
12250 GOTO 30000
15000 PRINT"J"
15010 POKE36869:240:POKE36879:232:PRINT"███":POKE36876:0:POKE36878:0:POKE36877:0
15020 PRINT"██████████TIME UP "
15025 PRINT"███YOU SCORE:███"
15030 INPUT"███ANOTHER GO?" :OF
15040 IF OF="Y" THEN RUN
15050 IF OF="N" THEN POKE650:0:END
15060 GOTO15020
30000 POKE52:28:POKE56:18:POKE51:0:CLR
30020 FOR I=0 TO 511
30030 POKE7169+I:PEEK(32768+I):NEXT
30040 FOR I=0 TO 7:READ J:POKE7169+I:J:NEXT
30050 DATA 0,153,100,80,155,60,60,66
30055 PRINT"███ ANY KEY TO START███"
30056 GET OF:IF OF="" THEN 30056
30060 GOTO20

```

```

2000 LET R=1/2
2010 LET S=1
2020 LET A=10
2030 LET B=A/A
2040 LET X=A(>A)
2050 LET Y=X
2060 LET Z=A+A
2070 FOR H=0 TO A
2080 LET N=A(>A)
2090 FAST
3000 FOR I=0 TO 40+250*RND
310 LET U=RND
320 PRINT " " AND U>=R;"█" AND
U<R:
330 IF U<R THEN LET N=N+B
340 NEXT I
350 SLOW
360 FOR I=A(>A) TO Z
370 NEXT I
380 CLS
390 INPUT E
400 PRINT E;" /":N
410 FOR I=A(>A) TO Z
420 NEXT I
430 LET X=X+N
440 LET Y=Y+ABS(N-E)
450 CLS
460 NEXT H
470 PRINT "SUCCESS RATE ";((X-Y)
)/X)%; " PER CENT"

```

## Flash counting By Dave Lawrence

attempts a success rating is then displayed.

The main interest of the program is not in its originality but in the simple way that it does, in one context at least, help you change the way you count and become more open to those flashes of intuition that turn out to have a high degree of accuracy.

Beginners should be looking for a score of somewhere around the 80 per cent mark, but for more practised users an average of 95 per cent is achievable.

### Program notes

**Line 200.** This value is used later to determine the frequency with which squares are printed. A higher value will result, on average, in more squares and vice-versa.

**Line 230.** This line and the three following save space by avoiding the use of literal numbers.

**Line 300.** There is nothing particularly significant about the maximum value of the loop, simply that if the full 290 print positions are used it is about the maximum display obtainable before the memory is full.

**Line 320.** On a 1K ZX81 it is always important to remember that print statements can be associated logically on the same program line. Here, the conditions associated with each print statement ensure that *either* a space is printed *or* a black square.

**Line 330.** N is the number in a particular group.

**Line 430.** X is the total number in all groups.

**Line 440.** Y is the total error, either way.

## Pie Chart

By Simon Lane

```

10 PRINT TAB 10,"PIE CHART"
20 PRINT TAB 10,"WHAT IS THE TITLE"
30 PRINT " "
40 INPUT T$
50 PRINT " "
60 IF LEN T$ <= 20 THEN GOTO 100
70 CLS
80 PRINT "SORRY, 20 CHARACTERS MAX."
90 GOTO 30
100 PRINT " "
110 PRINT "HOW MANY CATEGORIES"
120 INPUT N
130 PRINT " "
140 IF N <= 7 THEN GOTO 170
150 CLS
160 PRINT "SORRY, 7 CATEGORIES MAX."
170 GOTO 100
180 DIM N(N)
190 DIM P(N)
200 PRINT " "
210 PRINT "WHAT ARE THE UNITS"
220 INPUT U$
230 CLS
240 IF LEN U$ <= 5 THEN GOTO 250
250 PRINT "SORRY, 5 CHARACTERS MAX."
260 GOTO 100
270 PRINT " "
280 PRINT "CAT. NAME NO."
290 PRINT " "
300 PRINT " "
310 PRINT " "
320 PRINT " "
330 PRINT " "
340 PRINT " "
350 PRINT " "
360 PRINT " "
370 PRINT " "
380 PRINT " "
390 FOR K=1 TO 10
400 NEXT K
410 NEXT J
420 GOTO 320
430 LET N$(I)=X$
440 PRINT AT I+2,6,N$(I); " ?"
450 INPUT N(I)
460 LET T=T+N(I)
470 PRINT AT I+2,17,N(I)
480 NEXT I
490 FOR I=1 TO N
500 LET P(I)=N(I)/T*100
510 NEXT I
520 CLS
530 PRINT TAB 10,"LEN T$ / 2, T$ / TR"
540 PRINT " "
550 PRINT " "
560 PRINT " "
570 PRINT " "
580 PRINT " "
590 PRINT " "
600 PRINT " "
610 PRINT AT I+11,21,X$; " "
620 TAB 30;INT (P(I)+.5)
630 LET E=D+P(I)
640 IF I=N THEN GOTO 700
650 LET X=SIN (E/50*PI)+20
660 LET Y=COS (E/50*PI)+20
670 LET Z=ABS X
680 IF ABS Y > Z THEN LET Z=ABS Y
690 FOR J=0 TO Z
700 PLOT X/Z+J*20,Y/Z+J*20
710 NEXT J
720 PRINT AT 11,-COS ((D+E)/100*PI)+.75,SIN ((D+E)/100*PI)+.75
730 LET D=E
740 NEXT I
750 LET X$=STR$ T
760 PRINT AT I+11,25,"-----"
770 PRINT " "
780 PRINT " "
790 PRINT " "
800 PRINT " "
810 PRINT " "
820 PRINT " "
830 PRINT " "
840 PRINT " "
850 PRINT " "
860 PRINT " "
870 PRINT " "
880 PRINT " "
890 PRINT " "
900 PRINT " "
910 PRINT " "
920 PRINT " "
930 PRINT " "
940 PRINT " "
950 PRINT " "
960 PRINT " "
970 PRINT " "
980 PRINT " "
990 PRINT " "

```

## Pie chart

on ZX81

This program will draw a pie chart from any data you care to give it. First ask for a title. This must be a maximum of 20 characters, and will appear above the pie chart in the final display.

Next ask for the number of categories which must be a maximum of seven. Now ask for the units. This is the name of whatever units each category is measured in, for example people or days, and can have up to six characters.

Finally you are asked for the name and number in each category. The name may contain up to nine characters. The screen is then cleared and the pie chart is drawn. Note that the figures in the % column will not always add up to 100, due to rounding.

## Arithmetic

on ZX81

Two programs for the 1KZX81 for your children to practice their sums. The first program is for eight- to 11-year-olds and will accommodate both addition or subtraction. The second program for younger children, is shown for addition only, but can be easily adapted for subtraction, multiplication or division.

Both programs will just fit in 1K, but only at the expense of total lack of comments in the listing, and a primitive display. With 16K available, much more can be done.

In the listing in figure 4, the difficulty can be adjusted to match the child by altering the values in lines 60 and 70. The 10 gives one decimal place and the 1000 gives values up to 99.9. The routine at line 500 ensures that the decimal points line up. The answer is checked at line 240 and allows for the slight imprecision in the ZX81 holding decimal numbers (when converted to binary etc).

In the listing in figure 3, the difficulty is dependent on the values in lines 50 and 60. Lines 80-100 select four values near to the right answer and ensure that no two values are alike. Lines 110-120 selects one out of the four as the correct answer. The choice is selected randomly between a b c d.

## Arithmetic

By Roy Eastwood

### ADDITION OR SUBTRACTION

```

10 LET R=0
20 LET U=0
30 PRINT "A OR S?"
40 INPUT X$
50 CLS
60 LET A=INT (RAND*1000)/10
70 LET B=INT (RAND*1000)/10
80 IF X$="A" THEN GOTO 130
90 IF A > B THEN GOTO 130
100 LET D=A
110 LET A=B
120 LET B=D
130 LET Y$=STR$ A
140 GOSUB 500
150 LET Y$=" "
160 GOSUB 500
170 IF X$="A" THEN PRINT " +"
180 IF X$="S" THEN PRINT " -"
190 PRINT " "
200 LET D=A+B
210 IF X$="S" THEN LET D=A-B
220 LET Y$=STR$ D
230 GOSUB 500
240 INPUT Y$
250 PRINT AT 1,0;
260 GOSUB 500
270 IF ABS (VAL Y$-D) > .01 THEN
280 GOTO 100
290 LET R=R+1
300 PRINT "R=";R;" U=";U
310 PAUSE 150
320 IF R > 9 THEN STOP
330 GOTO 50
340 PRINT "WRONG"
350 LET U=U+1
360 PAUSE 150
370 CLS
380 GOTO 130
390 FOR N=1 TO LEN Y$
400 IF Y$(N)="" THEN GOTO 530
410 NEXT N
420 PRINT TAB 4-N;Y$;
430 RETURN

```

### ADDITION

```

10 LET R=0
20 LET U=0
30 DIM D(4)
40 PRINT "ENTER LETTER"
50 INPUT X$
60 LET A=1+INT (RAND*11)
70 LET B=1+INT (RAND*11)
80 PRINT A;"+";B;"=?"
90 PRINT " "
100 FOR N=1 TO 4
110 LET D(N)=A+B-2+INT (RAND*5)
120 IF D(N)=A+B THEN GOTO 90
130 FOR M=N-1 TO 1 STEP -1
140 IF D(M)=D(N) THEN GOTO 90
150 NEXT M
160 NEXT N
170 LET C=INT (RAND*4)+1
180 LET D(C)=A+B
190 FOR N=1 TO 4
200 PRINT CHR$ (37+N); " "
210 NEXT N
220 INPUT U$
230 PRINT U$
240 IF CODE U$ <= 37 THEN GOTO 100
250 LET R=R+1
260 PRINT "R=";R;" U=";U
270 PAUSE 150
280 IF R > 9 THEN GOTO 600
290 CLS
300 GOTO 30
310 PRINT "WRONG"
320 LET U=U+1
330 GOTO 150
340 PRINT AT 15,0;R;" / ";A+U

```

### ENTER LETTER

6+3=7

0: 11  
1: 10  
2: 7

### ENTER LETTER

6+4=7

0: 10  
1: 10  
2: 11

3  
R=2 U=1

# Spectrum

In this new slot various contributors explore different aspects of the ZX Spectrum.

## Take a look inside the ZX Spectrum

*Stephen Adams lifts the lid off the machine everyone's talking about*

The ZX Spectrum is basically a more advanced version of the ZX81 with more RAM memory within the computer and the ability to have colour plus a limited sound capacity.

There are 14 ICs in the case plus the familiar 1 amp, 5 volt voltage regulator. The eight RAM ICs give a total of 16K using the same chips as used in the Sinclair 16K RAM pack (which is not usable on the Spectrum).

Also included is the transformer (on the top right) which provides -5v, +12v and -12v for the RAM chips and is still buzzing away.

The two large chips on the right-hand side are the 16K ROM and the Z80A micro-processor.

Moving to the left we come to two 74LS157 chips which are used when refreshing the RAM, the big chip to the left side of these is the Universal Logic Array (ULA) which contains all the electronic bits which control colour display, memory decoding and refreshing.


Above the RAM chips is the colour encoding circuitry and its crystal, plus the crystal for the micro-processor which runs at 14Mhz. The ULA however divides this down to 3.5Mhz before it gets to the Z80R.

These crystals both have capacitor 'trimmers' which can be adjusted to keep the frequency correct and this makes the timing more accurate than the ZX81, which used a ceramic filter to control the frequency.

On the far left-hand side below the video modulator (the metal box) is the PAL encoding IC which allows you to put colours on the TV picture.

At the back are three sockets: +9 volt power (a barrel socket on the review model we had, unlike the Jack Plug socket shown in the picture), MIC and EAR sockets.

There is also the edge connector which now has 28 metal strips on both sides, unlike the ZX81 which only had



What you get when you take the cover off the new ZX Spectrum.

23. This means that only input/output ports 'may' work on the Spectrum.

The memory map is entirely used up by the ROM and RAM and only the ROM CS line appears on the edge connector. This means that any memory mapped devices will have to be redesigned.

The edge connections are shown below and the ones that are different from the ZX81 are marked with an asterisk.

Top of connector:	Bottom of connector:
1 A15*	A14*
2 A13*	A12*
3 D7	+5v
4 UNUSED	+9v
5 SLOT	
6 D0	0v
7 D1	0v
8 D2	CK
9 D6	A0
10 D5	A1
11 D3	A2
12 D4	A3
13 INT	IORQGE*
14 NMI	0v*
15 HALT	VIDEO
16 MREQ	Y*
17 IOREQ	V*
18 RD	U*
19 WR	BUSREQ*
20 -5v*	RESET*
21 WAIT	A7
22 +12v*	A6
23 -12v*	A5
24 MI	A4
25 REFRESH	ROM CS
26 A8*	BUSACK*
27 A10*	A9*
28 UNUSED	A11*

The keyboard plugs into two sockets as before so that other keyboards fitted to the ZX81 should work. The only other sockets left on the board

are two empty IC sockets to allow the 32K internal RAM board to plug into the Spectrum.

The left-hand side socket contains the address lines and the right-hand one the data and control lines. This extra board will convert a 16K Spectrum into a 32K one and costs £60.

I was unable to test the tape interface or explore the IN and OUT commands as the review model overheated after half an hour and so no program of any length could be put in. However, I have since heard of several Spectrums performing quite happily for longer periods, so it would appear we had a bad machine.

The signs of overheating were colours mixing together on the screen, corruption of the program in RAM, plus the system going back to showing the copyright line (this usually appears on starting up the machine).

The IN and OUT commands are a very useful way of getting information via Basic out to an external device, but although there are said by Sinclair's manual to be 64K of them, less than 256 are available to the programmer.

### Conclusions

The ZX Spectrum will prove an interesting challenge to the manufacturers who are at the moment supplying products for the ZX81.

For the user it means that again Sinclair has imposed a great deal of restrictions on what hardware can be used with the machine.

# Programming

## Keys which unlock the most potential

*Nick Hampshire tells you how to get the most from Vic-20's function keys*

On the right-hand side of the Vic-20 keyboard there are four special keys known as function keys. By using these keys in both shifted and unshifted mode they can be used to define up to eight different functions.

Unfortunately Commodore has not provided any Basic commands on the standard Vic to utilise these keys, you must consequently develop your own routines.

In order to use the function keys one needs to understand the way in which the Vic system software detects a key depression. The Vic does this with a keyboard scanning routine which is called 60 times per second by an interrupt generated by one of the internal timers on the I/O chips.

The keyboard scanning routine is very simple and scans all the keys,



Keys... to greater options.

including the four function keys, looking for a key which has been pressed. The keyboard is organised as an 8x8 matrix with the keys at the intersection points of the vertical and horizontal lines.

The vertical lines are connected to an eight-line output port and the hori-

zontal lines to an eight-line input port. If a key is pressed then an output line is connected to an input line, with just one combination of input/output line for every key.

To scan the keyboard the computer sets just one of the output lines at a time low, while keeping the rest high, then tests the input port to see if any of the input lines are low. This is repeated eight times for each output line.

If one of the input lines is found to be low then a key depression is detected and the keyboard scanning software determines which key was pressed.

This key is first assigned a number which is stored in location 203 prior to being decoded by the input routine and given an Ascii code value.

When dealing with the function keys we are interested in the value stored in location 203, we are also interested in the status of the shift key, this is stored in location 563.

### Learning the values

By looking at the contents of location 203 we find that the function keys have been assigned the following values, remember that the value in 203 for the shifted and unshifted key will be the same:

function key #1 & #2 — 39  
function key #3 & #4 — 47  
function key #5 & #6 — 55  
function key #7 & #8 — 63

The shift key in location 653 has the following status:

shift unpressed — 0  
shift pressed — 1  
CBM pressed — 2  
CBM and shift pressed — 3

The routine (left), uses these values to test which function key has been pressed. It should be noted that although the Vic is only designed to have eight function keys this could be increased to 12 or even 16 by using the CMB and CBM shift keys in addition to pressing one of the four function keys.

This would mean that each function key could have up to four different assignments depending on whether the shift, CBM or both were also pressed.

```
1 REM #ROUTINE TO TEST WHICH FUNCTION
2 REM #KEY HAS BEEN PRESSED
3 REM
4 REM
8 REM #WHICH KEY PRESSED?
9 REM
10 A=PEEK(203)
11 REM
12 REM #SHIFT KEY DOWN?
14 REM
15 B=PEEK(653)
16 REM
17 REM #DECODE KEY NUMBER
18 REM
20 K=0
25 IF A=39 THEN K=1 : GOTO 50
30 IF A=47 THEN K=3 : GOTO 50
35 IF A=55 THEN K=5 : GOTO 50
40 IF A=63 THEN K=7 : GOTO 50
45 GOTO 10
50 IF B>1 THEN B=0
55 K=K+B
60 PRINT "FUNCTION KEY ";K;" PRESSED"
65 GOTO 10
```

# Sound & vision



## Giving soul to electronic music

Microcomputer-based musical instruments are appearing all over the place these days. In the music charts, a number of performers use them as an integral part of their sound. Others have their sound based on micro generated music.

Depeche Mode is one group who use fast sequences to provide a backdrop for their imaginative new pop.

At the other end of the spectrum are big international stars like Vangelis who provided the theme music for the film *Chariots Of Fire*, and the Frenchman Jean-Michel Jarre, whose *China Concerts* were recently shown on television.

Critics say that this kind of electronic music has no soul, that anything based on the output of a microcomputer has not got

expression. This is of course denied by the music the performers produce.

Most professional electro-musicians have very expensive equipment which enables them to express musical ideas fully. It is possible to use some of their techniques at home, to produce more interesting computer music.

There are a number of qualities that go to make up what we refer to as music. Harmony, rhythm and timbre are the main ones.

The timbre of a sound is closely related to its volume envelope. On a synthesiser there is often a set of controls referred to as envelope. It can be used to control the amplitude of the complete sound, being triggered by the initial depression of a key.

In a similar way it can be used to control the amount of filtering given to the sounds present at the output of the mixer.

Of course some synthesisers allow you to control both the volume and the filtering with the envelope, although only the most expensive machines allow you to define separate envelopes for each.

The Roland SH-09 synthesiser even allows you to define the pulse-width with the envelope, enabling interesting 'phased' effects.

The timbre of a sound is the shape of the wave of a sound. This wave is the one that defines the pitch of the sound, and it has a shape that contains other frequencies giving it a distinct sound.



Sequencer ... Jean Michel Jarre.

For example, a simple square wave sounds a little like a woodwind instrument, a sawtooth wave like brass instruments.

On a sophisticated machine the timbre envelope can be defined just like the others. Thus an envelope varies a quantity over a time.

Here is the snort outline of a program that defines a volume envelope on the Vic-20:

```
10 dim a(10)
20 FOR I=1 TO 10: INPUT a(I): NEXT I
30 POKE 36874, 221: REM TEST NOTE
40 FOR I=1 TO 10: POKE 36878, a(I): FOR J=1 TO
25: NEXT J: NEXT I
50 POKE 36878,0
```

This program should give you an idea. If you think you can improve on it send your program (Vic, Atom, BBC, or Sinclair) to me, Sam Blyth, care of *Popular Computing Weekly*. The best submission will win a record album token.

Sam Blyth



## Seeing red when the word is blue

So far we've learnt that it is possible to draw not just a circle — or at least a polygon approximating one — but also how to use that graphic information to do other things. This week, we'll take a look at something that is often neglected — the graphic use of text.

The reason this is seldom referred to is not hard to pinpoint: most computers just can't do it. Most machines only allow you a certain number of places to put text.

Two exceptions are the Research Machines 380Z (so long as you use their

level 2 graphics version of Basic, called Basic SG2) and the BBC machine. Doubtless there are others; doubtless you will write to tell me so.

Though you can't easily alter the size of text on the BBC machine, you can alter position and colour. For example, you can print the word RED in blue somewhere on the left of the screen, and the word GREEN, in yellow, somewhere near the top.

(Incidentally, adults and children differ markedly in their ability to sense quite what is 'wrong' about such a display.)

One of the BBC Basic's VDU commands, VDU5, links the text and graphics 'cursors', or conceptual pencils, which are normally quite separate. You don't usually want your questions to a graphics user appearing next to or even on top of the image.

Here, however, we'll make a virtue of that. When you want to stop, VDU4 returns things to normality.

First of all, get into mode 5 graphics, which gives four colours and 160\*256 points (though remember you always address them as if you had a thousand — the machine scales them down for you.) Then type VDU5.

Now, use the move command, with an X and a Y value (500,500 would be near the centre) to move the graphics (and hence the next) cursor to that point. Then, just print something, like 'hello' — it will appear at the current position (exactly) and in the current graphics colour (which you can change using the GCOL command).

You'll probably have seen the point already: it is that you can, by this method, cause text to be placed all over the screen. The position of the text is determined by the graphics cursor. So any program that generates images can, instead (or as well) be used to place text.

Remember that if the text is plotted very close to the last lot, you may just get a blurred, 'blocky' effect (maybe you wanted that — it's called a creative mistake).

Try this with the circle program from last week, missing out all the plot commands except move, and just printing something. If you can find routines that will produce sine curves or lissajous figures, try linking the text to them.

Then, you could link in the sound as well, so that the frequency of the note was determined by the vertical position of the graphics cursor on the screen ...

And so on.

Brian Reffen Smith

# Our classifieds are faster.

Do you want to sell your computer and buy a bigger and better one?

Have you ever thought of trying to make some money out of selling tapes of your own programs?

Whatever it is you want to buy or sell why not use our classified pages?

It has to be better than waiting for up to nine weeks to get into one of the old monthly magazines.

Not only that, but our rates are very reasonable.

For private individuals it only costs 20p per word, with a minimum of 10 words.

We can make it so cheap because we charge companies using the classified columns 40p per word.

The classified pages can be used for semi-display advertising.

The cost for this is £10 per single column centimetre, with a minimum charge of £30.

All copy for the classified pages must be pre-paid. (You'll find a handy form on page 22).

Cheques and postal orders should be made out to *Popular Computing Weekly*. Your advertisement should arrive at least two weeks before the publication date.

If you have any queries regarding classified advertising please call 01-839 1855.

For semi-display advertising, please call David Lake on 01-839 2846.

**Popular Computing Weekly.**  
The fast one.

# Hand & mouth



## Sharp's mini goes for the wallet

Sharp, the Japanese based calculator firm, has just launched what must be the most advanced mini calculator/computer on the market.

Equipped with the new printer/cassette interface, the mini-computer comes in a brown briefcase sized wallet which would not even fit into a Texan's pocket. The PC 1500 supersedes, and at first glance looks identical to, the PC 1211.

The total amount of random access memory has been increased to 3.5K (as opposed to the 1211's 1.9K) with 1850 bytes available in Basic program and data memory.

The RAM can be expanded by the addition of a 4K or 8K CMOS memory

module, and programs stored on up to two cassette tape recorders simultaneously.

Lest you obtain the false impression that this is just a PC 1211 Mark Two let me point out the significant differences.

The now standard Sharp QWERTY keyboard has six very useful user definable keys which can be operated as anything from reservable function and command keys to the control of games on the display. The latter is possible on the 7 x 156 dot liquid crystal display since each dot is individually addressable, leading to Sharp's advertising of a 'multi-graphic display area'.

There are a host of new Basic commands available to the user which especially improve string handling and enable two dimensional array manipulation. Some of the new commands are directed to-


wards the CE 150 printer which gives the best output I've seen from a 'pocket' model.

The secret lies in a really quite advanced four colour graphic package which enables the user to chose nine different sizes of characters and lines ranging from four to 36 digits in length.


Virtually any pattern may be displayed on the 58mm wide paper as the printing head can be controlled completely in all four directions.

Of course there's always a hitch somewhere. In this case it is the price, which though probably justifiable, takes this machine into the range of the micro-computer. At around £150 for the basic model and (a similar sum for) the printer/cassette interface I'd stick my neck out and go for a micro.

John Gowrie



Sharp's PC1500 pocket computer with printer and printer cassette interface.



## Just remember... you are human!

Last week's questions should help you to examine assembler programs more critically and in this week's article I describe some more points to watch out for. Remember you are unlikely to need all the features that could be included.

Asimov, the word processor I use to write with, is over seven kilobytes of machine code assembled from more than 3,500 lines of source code. The assembler I used is quite simple and I didn't use all of its facilities in the seven months it took to construct Asimov.

Let me repeat one key idea from last week — the human factors in the engineering of the assembler are crucially important. You will spend a great deal of

time typing source code and editing, extending, and correcting after the first trial assembly.

How easy are the controls to move the screen window over the source code held in memory? Ideally you should be able to use one single keystroke to move down the listing and another to move up.

Can you alter the number of lines that you move in one bound, for example?

Can you insert letters and words into a line of text or must you type the line again to alter it?

You will be able to delete one line of the program but can you also delete a block of lines and is the method for doing that easy to remember and carry out?

Is it possible to copy one or more lines from one part of the program to another? This facility is the basis of a macro-assembler and I will write more about that later.

Will the assembler cope with different number bases, that is, can you enter numbers in decimal, hexadecimal and octal notation? The first two bases are the most important for microcomputers now current in this country.

To which base does the assembler default? If you are familiar with hexadecimal for addressing Random Access Memory (RAM) then you will find decimal very strange and vice versa.

Some assembler programs allow you to write a mathematical expression in place of the operand, that is the address or label following the CPU instruction. The Micro-tanic Software assembler allows you to add or subtract while ZEN offers addition, subtraction, multiplication, division, and logical AND and OR.

How easy is it to define bytes and words that you wish to use as constant numbers and variables in your program? For example the Micro-tanic Software assembler for the Tangerine uses the following 'pseudo-op codes' (that is an instruction that is recognised by the assembler but which is not in the CPU instruction set) among others:

BYT — Defines a single byte value in memory eg 20 Hex. which equals a space on the VDU.

WOR — Defines a two byte value eg FC00 Hex, the start of the TANBUG monitor.

EQU — This instruction assigns a value to a label. For example, the instruction:

```
PRINT EQU SA794
```

followed in the course of the program by the instruction:

```
JSR PRINT
```

would cause the assembler to generate machine code that will jump to a sub-routine at the address A794 Hex.

John Dawson

# POPULAR Computing WEEKLY

HOBHOUSE COURT, 19 WHITCOMB STREET WC2

## WHY NOT TAKE OUT A SUBSCRIPTION?

You can have *Popular Computing Weekly* sent to your home for £19.95 a year. This will cover the cost of the magazine, postage and packing.

Fill in the coupon below and keep yourself up to date week by week.

I would like to take out ..... subscription(s) to *Popular Computing Weekly*.

Name .....

Address .....

Tel No. ....

I enclose £..... for ..... subscription(s).

Please make cheques payable to Sunshine Publications Ltd.

## STOP PRESS ZX81 16K RAM

(AS ADVERTISED IN COMP./VIDEO GAMES)

NEW LOW PRICE!

# £19.95 inc.

FULLY COMPATIBLE, BLACK CASE, GOLD CONNECTOR.

■ ASSEMBLED \_ TESTED \_ GUARANTEED ■

Cheque/POs to:  
PLESSIS ELECTRONICS, CASTLE HOUSE, OLD RD,  
LEIGHTON BUZZARD (beds), LU7 7RG.

### 7 DAYS DELIVERY

## ZX HARDWARE....

### PROFESSIONAL 40 KEY KEYBOARD

- All legends and graphics in 2 colours
- No soldering to ZX81, just plug in
- Proper typewriter keys
- RAM/Printer compatible

Kit £19.95 Built £24.95 Case £10.20  
Repeat key add on TBA

Range of in/out ports, music boards, motherboards,  
D to A converter boards. Write for catalogue

23 way double sided, gold female edge connector,  
wirewrap type £2.95

Male connector £1.25

Ribbon cable £1.40 per metre

Mastering Machine code book £5.50

Programming for real applications £6.50

Tape for real applications £11.25

### HARRIS & LOCKYER ASSOCIATES

(Sole distributors for Redditch Electronics)

Dept PW Prices include VAT + P&P  
33 Pedmore Close Overseas add £1.80 postage  
Woodrow South Delivery 3 days for in stock  
Redditch items else allow 28 days  
Worcs  
Tel: (0527) 24452 Official orders welcome

# Peek & poke

Peek your problems to our address. Ian Beardsmore will poke back an answer.

## AND A BIG, BIG HAND FOR THE WINNER!

Malcolm Fraser of Stone Lane, Kinver, writes:

**Q** I have a BBC Model A Microcomputer and have written a number of games in which the computer plays against me. What irks, though, is having to accept such low-key salutes as 'YOU WON, CONGRATULATIONS!' which I find a let-down at the end of a long game. Could you suggest a way, or ways, of ending the program more dramatically, please?

**A** If you add the following routine, or some variation, to the end of your program, it will print an endless series of the word 'Congratulations!' in double-height, randomly coloured letters, at random positions on the screen, while at the same time making an extraordinary cacophonous noise.

```
10 REM*END OF GAME DEMO*
20 MODE 7
30 REPEAT
40 A=RND(16):B=RND(16)
50 PRINTTAB(A,B):CHRS(141);
   CHRS(128+RND(6));
   "Congratulations!"
60 PRINTTAB(A,B+1):CHRS(141);
   CHRS(128+RND(6));
   "Congratulations!"
70 SOUND RND(4)-1,-15,
   RND(128)+127,RND(29)
80 UNTIL FALSE
```

## HOW DO I POKE THE COLOUR ON MY VIC?

Kenneth Toomey of Milton Court, London, EC2 writes:

**Q** I have only had my Vic-20 for a couple of weeks and have had great difficulty understanding the information given in the manual on how to put colour where I want it on the screen. I learnt about peek and poke at school, using a ZX81, but what I've found out there doesn't seem of any use whatsoever for getting colour on to the screen. I would be pleased if you could indicate how the whole thing works, as I believe PEEK and POKE are much better ways of manipulating the screen than just using PRINT statements.

**A** The simplest way to poke colour into the screen — keeping in mind that you must

poke a character into the screen using one set of addresses, and then poke the colour for that character into place with what appears to be a completely different set of addresses — is to realise that there is a clear mathematical relationship between the two addresses. As you can tell from the charts in the back of your manual, the first screen address is 7680, for poking characters, while the first screen address for colour is 38400, ie 30720 more.

I suggest you work out your program just using the character codes, and once that is working satisfactorily without colour, add the colour POKE commands, working them out by adding 30720. Another way of doing this is to put both controls within a loop.

Enter and run the following routine, which comes from the book *Symphony For A Melancholy Computer* and you'll see the process at work:

```
10 FOR Q=8032 TO 8119
20 POKE Q, 102
30 POKE Q+38752-8032, 5
40 NEXT Q
```

## MEMORIES ARE MADE OF THIS, PART ONE

Malcolm Arnett of Jedburgh Drive, Warrington writes:

**Q** I have read from time to time of apparent problems that people have had with 16K packs on their ZX81s. Have these been solved or is there a recurrent problem with the RAM pack? I need to know before I spend £49.95 — which I can barely afford — on a Sinclair memory pack.

**A** The Sinclair 16K pack has, it is true, had pretty bad press in the past due to its habit of — in many cases — dumping everything so you lose the program, appearing to 'shrink' so variables are overwritten, or even actually falling off the back of the ZX81 while you are attempting to program.

Most of these problems can be overcome by removing the back of the RAM pack so it stays cool; cleaning the contacts with surgical spirit before you attach the memory; and using Blu-tack or a similar

product to firmly fix the pack in place.

If you are not willing to go to these lengths — and there are many owners of 16K RAM packs bought from Sinclair who have not had to do such things — you could buy a memory expansion kit from someone else. First ask yourself how much memory you really need. Quicksilver, among others, supply a very cheap — around £15 — 3K pack which makes the computer much more useful than it is with just the 1K.

If you need more, you could choose from a number of reputable suppliers, which include Phoenix Marketing (£34.95 for 16K), JRS Software (£35), and dK Tronics (16K kit — £32.95, 4K — £22.95, 2K — £15.95).

## MEMORIES ARE MADE OF THIS, PART TWO

Geoff Ross of Highlands Way, London NW7 writes:

**Q** Why are REM statements used in programs at the start, when they don't do anything?

**A** A REM statement at the start of a program is usually used as storage space for a machine code routine. Because the computer ignores REM statements, it effectively starts the program at the first conventional statement. Information in the REM statement can then be accessed later. REM statements are usually put at the start of a program, because there is nowhere for them to move within the RAM. The space they create is therefore always in the same place, which of course makes it much easier to use.

## PRINT 'THIS IS THE WRITE ADDRESS'

David Hole of The Dell, Ashford, Kent writes:

**Q** I want to send back my printer because I think it is faulty, but though Sinclair Research is based in Cambridge, they have another address in Camberley, Surrey. To which address should I send my printer?

**A** The address you want is Sinclair Research (JRS),

Stanhope Road, Camberley, Surrey, GU15 3PS. This is the address of Sinclair's mailing company which deals with all dispatch and returns. In fact I gave out this address a couple of weeks ago, so you might well know it by now.

## A BIGGER APPETITE MEANS BIGGER BYTES

Kathy Stewart of Hill End Lane, Windsor writes:

**Q** Is it true that a program on the ZX81 uses a great many more bytes than the same program on the ZX80?

**A** In many cases yes. The program below will use more than twice the number of bytes on the ZX81 than on the ZX80. Even with careful programming it is virtually impossible not to use more bytes on the ZX81.

```
10 LET A=6
20 DIM B (6)
30 LET C=RND(12)
   on the ZX81 enter ...
30 LET C=INT(RND*12)+1
```

## HERE'S A BUNCH OF ODD CHARACTERS

Barry Keats of Arbour Lane, Harlow, Essex writes:

**Q** Is there a program that shows you the set of characters which the ZX81 has? I get fed up looking through books to find the list of them.

**A** Try the following . . .

```
10 LET A=PEEK 16509
20 PRINT "INPUT CHARACTER NUMBER"
30 INPUT C
40 PRINT CHRS C
```

This does what you want it to do, but there is a lot more scope if you add the following:

```
40 PRINT CHRS C;"-";C;" ";
50 LET C=C+1
60 INPUT BS
70 IF BS="S" THEN STOP
80 IF BS="N" THEN GOTO 30
90 IF BS="R" THEN GOTO 40
```

'S' will simply STOP the program. 'N' lets you put in any new number. 'R' will PRINT out the next symbol and number after the one you have just entered.

Send your questions to Peek & poke, Popular Computing Weekly, Hobhouse Court, 19 Whitcomb Street, London WC2 7HF.





SEE VIC AT THE INTERNATIONAL  
COMMODORE COMPUTER SHOW,  
CUNARD HOTEL, HAMMERSMITH,  
3rd-5th JUNE.  
3rd June 12 noon-6pm. 4th June 10am-6pm.  
5th June 10am-5pm.



# “Give me one good reason why I should choose a VIC 20 home computer.”

1. VIC is outstanding value for money. No other colour home computer can give so much for under £200.

2. Total standard memory 25K made up of 20K ROM and 5K RAM.

3. Fully expandable to 27½K user RAM.

4. Microsoft Basic interpreter as standard.

5. Accessible machine language via plug-in cartridges.

6. Connects direct to monitor or standard television.

7. Full size typewriter style keyboard.

8. Full colour and sound.

9. All colours easily accessible.

10. 62 predefined graphic characters direct from the keyboard.

11. Full set of upper and lower case characters.

12. 256 displayable characters direct from the keyboard.

13. High resolution graphics capability via plug-in cartridges.

14. Programmable function keys can be used with plug-in cartridges.

15. Automatic repeat on cursor function keys.

16. User-definable input/output port.

17. Machine bus port for memory expansion and ROM software.

18. Standard interfaces for hardware peripherals.

19. VIC 20 is truly expandable into a highly sophisticated computer system with a comprehensive list of accessories (see panel below).

20. Full range of software for home, education, business and entertainment on disk, cassette and cartridge.

21. Books, manuals and learning aids from Teach Yourself Basic to the VIC programmers' reference guide (a must for advanced programmers).

22. Full support for VIC owners – their own magazine 'VIC Computing' as well as a national network of VIC user groups.

23. National dealer network providing full service and support to VIC owners.

24. Expertise and experience – Commodore are world leaders in microcomputer and silicon chip technology.

25. Commodore is the leading supplier of micro computers in the UK to business, schools, industry and the home.

26. VIC 20 is the best-selling colour home computer in the UK.

How many reasons was it you wanted?

#### Accessories include:

- Cassette tape unit.
- Single drive 5¼" floppy disk unit (170 K bytes capacity).
- 80-column dot matrix printer.
- 3K, 8K and 16K RAM expansion cartridges.
- Programming aid packs, machine code monitor cartridge, programmers' aid cartridge, high resolution graphics cartridge.

- Plug-in conversion box for a full 32K, 40-column x 24 lines VIC including Prestel compatibility.
- RS 232C communication cartridge.
- Memory expansion board.
- IEEE488 interface cartridge.
- Joysticks, light pens, paddles and motor controllers.

 **commodore**

## VIC 20

**The best home computer  
in the world.**